

Internet Engineering Task Force (IETF)  
Request for Comments: 7147  
Obsoletes: 4544  
Category: Standards Track  
ISSN: 2070-1721

M. Bakke  
Dell  
P. Venkatesen  
HCL Technologies  
April 2014

Definitions of Managed Objects  
for the Internet Small Computer System Interface (iSCSI)

**Abstract**

This document defines a portion of the Management Information Base (MIB) for use with network management protocols. In particular, it defines objects for managing a client using the Internet Small Computer System Interface (iSCSI) protocol (SCSI over TCP).

This document obsoletes RFC 4544.

**Status of This Memo**

This is an Internet Standards Track document.

This document is a product of the Internet Engineering Task Force (IETF). It represents the consensus of the IETF community. It has received public review and has been approved for publication by the Internet Engineering Steering Group (IESG). Further information on Internet Standards is available in Section 2 of RFC 5741.

Information about the current status of this document, any errata, and how to provide feedback on it may be obtained at <http://www.rfc-editor.org/info/rfc7147>.

**Copyright Notice**

Copyright (c) 2014 IETF Trust and the persons identified as the document authors. All rights reserved.

This document is subject to BCP 78 and the IETF Trust's Legal Provisions Relating to IETF Documents (<http://trustee.ietf.org/license-info>) in effect on the date of publication of this document. Please review these documents carefully, as they describe your rights and restrictions with respect to this document. Code Components extracted from this document must include Simplified BSD License text as described in Section 4.e of the Trust Legal Provisions and are provided without warranty as described in the Simplified BSD License.

This document may contain material from IETF Documents or IETF Contributions published or made publicly available before November 10, 2008. The person(s) controlling the copyright in some of this material may not have granted the IETF Trust the right to allow modifications of such material outside the IETF Standards Process. Without obtaining an adequate license from the person(s) controlling the copyright in such materials, this document may not be modified outside the IETF Standards Process, and derivative works of it may not be created outside the IETF Standards Process, except to format it for publication as an RFC or to translate it into languages other than English.

## Table of Contents

1. The Internet-Standard Management Framework .....	4
2. Introduction .....	4
3. Relationship to Other MIB Modules .....	4
4. Relationship to SNMP Contexts .....	5
5. Differences from RFC 4544 .....	5
6. Discussion .....	6
6.1. iSCSI MIB Object Model .....	7
6.2. iSCSI MIB Table Structure .....	8
6.3. iscsiInstance .....	9
6.4. iscsiPortal .....	9
6.5. iscsiTargetPortal .....	10
6.6. iscsiInitiatorPortal .....	11
6.7. iscsiNode .....	12
6.8. iscsiTarget .....	12
6.9. iscsiTgtAuthorization .....	12
6.10. iscsiInitiator .....	13
6.11. iscsiIntrAuthorization .....	13
6.12. iscsiSession .....	13
6.13. iscsiConnection .....	14
6.14. IP Addresses and TCP Port Numbers .....	14
6.15. Descriptors: Using OIDs in Place of Enumerated Types .....	15
6.16. Notifications .....	15
7. MIB Definition .....	16
8. Security Considerations .....	88
9. IANA Considerations .....	89
10. References .....	89
10.1. Normative References .....	89
10.2. Informative References .....	91
11. Acknowledgments .....	91

## 1. The Internet-Standard Management Framework

For a detailed overview of the documents that describe the current Internet-Standard Management Framework, please refer to section 7 of RFC 3410 [RFC3410].

Managed objects are accessed via a virtual information store, termed the Management Information Base or MIB. MIB objects are generally accessed through the Simple Network Management Protocol (SNMP). Objects in the MIB are defined using the mechanisms defined in the Structure of Management Information (SMI). This memo specifies a MIB module that is compliant to the SMIv2, which is described in STD 58, RFC 2578 [RFC2578], STD 58, RFC 2579 [RFC2579] and STD 58, RFC 2580 [RFC2580].

## 2. Introduction

This document defines a MIB module for iSCSI [RFC7143], used to manage devices that implement the iSCSI protocol. It obsoletes RFC 4544 [RFC4544].

The key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "NOT RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in [RFC2119].

## 3. Relationship to Other MIB Modules

The iSCSI MIB module is normally layered between the SCSI MIB module [RFC4455] and the TCP MIB module [RFC4022], and it makes use of the IP Storage (IPS) Identity Authentication MIB module [RFC4545]. Here is how these modules are related:

SCSI MIB      Within systems where a SCSI layer is present, each `iscsiNode`, whether it has an initiator role, target role, or both, is related to one SCSI device within the SCSI MIB module. In this case, the `iscsiNodeTransportType` attribute points to the SCSI transport object within the SCSI MIB module, which in turn contains an attribute that points back to the `iscsiNode`. In this way, a management station can navigate between the two MIB modules. In systems where a SCSI layer is not present, such as within an iSCSI proxy device, the `iscsiNodeTransportType` attribute points to the appropriate corresponding object within the appropriate MIB or is left blank.

TCP MIB	Each iSCSI connection is related to one transport-level connection. Currently, iSCSI uses only TCP; the iSCSI connection is related to a TCP connection using its normal (protocol, source address, source port, destination address, destination port) 5-tuple.
AUTH MIB	Each iSCSI node that serves a target role can have a list of authorized initiators. Each of the entries in this list points to an identity within the IPS Identity Authentication MIB module that will be allowed to access the target. iSCSI nodes that serve in an initiator role can also have a list of authorized targets. Each of the entries in this list points to an identity within the IPS-AUTH MIB module to which the initiator should attempt to establish sessions. The IPS-AUTH MIB module includes information used to identify initiators and targets by their iSCSI name, IP address, and/or credentials.

This MIB module imports objects from RFCs 2578 [RFC2578], 2579 [RFC2579], 2580 [RFC2580], and 3411 [RFC3411]. It also imports textual conventions from the INET-ADDRESS-MIB [RFC4001].

#### 4. Relationship to SNMP Contexts

Each non-scalar object in the iSCSI MIB module is indexed first by an iSCSI instance. Each instance is a collection of nodes, portals, sessions, etc., that can define a physical or virtual partitioning of an iSCSI-capable device. The use of an instance works well with partitionable or hierarchical storage devices and fits in logically with other management schemes. Instances do not replace SNMP contexts; however, they do provide a very simple way to assign a virtual or physical partition of a device to one or more SNMP contexts, without having to do so for each individual node, portal, and session row.

#### 5. Differences from RFC 4544

[RFC7143] updates several RFCs, including [RFC3720]. This document updates the iSCSI MIB correspondingly. The document uses `iSCSIProtocolLevel` as defined in [RFC7144]. It obsoletes [RFC4544]. Below is a brief description of the changes.

- Added `iscsiInstXNodeArchitecture` to `InstanceAttributes`.
- Added `iscsiSsnTaskReporting` of type BITS to `SessionAttributes`.
- Added `iscsiSsnProtocolLevel` to `SessionAttributes`.
- Deprecated the marker objects.
- Fixed the errata to [RFC4544].

- Added NOP counters at iSCSI session scope for heartbeat tracking.
- Added port number to the iscsiTgtLoginFailure and iscsiIntrLoginFailure notifications, and to the last failure info in iscsiInitiatorAttributesEntry.
- Added description string to the iSCSI portal.
- Added iscsiInstSsnTgtUnmappedErrors to support "Target Unmapped" session failure reporting in the iscsiInstSessionFailure notification.
- Added iscsiTgtLogoutCxnClosed and iscsiTgtLogoutCxnRemoved, which maintain the count of Logout Command PDUs received by the target with reason codes 1 and 2, respectively.
- Changed the conformance statements to match the above.

## 6. Discussion

This MIB module structure supplies configuration, fault, and statistics information for iSCSI devices [RFC7143]. It is structured around the well-known iSCSI objects, such as targets, initiators, sessions, connections, and the like.

This MIB module may also be used to configure access to iSCSI targets, by creating iSCSI portals and authorization list entries.

It is worthwhile to note that this is an iSCSI MIB module and as such reflects only iSCSI objects. This module does not contain information about the SCSI-layer attributes of a device. If a SCSI layer is present, the SCSI MIB module [RFC4455] may be used to manage SCSI information for a device.

The iSCSI MIB module consists of several "objects", each of which is represented by one or more tables. This section contains a brief description of the object hierarchy and a description of each object, followed by a discussion of the actual table structure within the objects.

### 6.1. iSCSI MIB Object Model

The top-level object in this structure is the iSCSI instance, which "contains" all of the other objects.

```

iscsiInstance
    -- A distinct iSCSI entity within the managed system.
    iscsiPortal
        -- An IP address used by this instance.
        iscsiTargetPortal
            -- Contains portal information relevant when the portal
            -- is used to listen for connections to its targets.
        iscsiInitiatorPortal
            -- Contains portal information relevant when the portal
            -- is used to initiate connections to other targets.
    iscsiNode
        -- An iSCSI node can act as an initiator, a target, or both.
        -- Contains generic (non-role-specific) information.
    iscsiTarget
        -- Target-specific iSCSI node information.
        iscsiTgtAuth
            -- A list of initiator identities that are allowed
            -- access to this target.
    iscsiInitiator
        -- Initiator-specific iSCSI node information.
        iscsiIntrAuth
            -- A list of target identities to which this initiator
            -- is configured to establish sessions.
    iscsiSession
        -- An active iSCSI session between an initiator and
        -- target. The session's direction may be Inbound
        -- (an outside initiator to the target represented by
        -- this node) or Outbound (the initiator represented by
        -- this node to an outside target).
    iscsiConnection
        -- An active TCP connection within an iSCSI session.

```

An iSCSI node can be an initiator, a target, or both. The iSCSI node's portals may be used to initiate connections (initiator) or listen for connections (target), depending on whether the iSCSI node is acting as an initiator or target. The iSCSI MIB module assumes that any target may be accessed via any portal that can take on a target role, although other access controls not reflected in the module might limit this.

## 6.2. iSCSI MIB Table Structure

Each iSCSI object exports one or more tables: an attributes table, and zero or more statistics tables, which augment the attributes table. Since iSCSI is an evolving standard, it is much cleaner to provide statistics and attributes as separate tables, allowing attributes and statistics to be added independently. In a few cases, there are multiple categories of statistics that will likely grow; in this case, an object will contain multiple statistics tables.

```

iscsiObjects
  iscsiDescriptors
  iscsiInstance
    iscsiInstanceAttributesTable
    iscsiInstanceSsnErrorStatsTable
      -- Counts abnormal session terminations
  iscsiPortal
    iscsiPortalAttributesTable
  iscsiTargetPortal
    iscsiTgtPortalAttributesTable
  iscsiInitiatorPortal
    iscsiIntrPortalAttributesTable
  iscsiNode
    iscsiNodeAttributesTable
  iscsiTarget
    iscsiTargetAttributesTable
    iscsiTargetLoginStatsTable
      -- Counts successful and unsuccessful logins
    iscsiTargetLogoutStatsTable
      -- Counts normal and abnormal logouts
  iscsiTgtAuthorization
    iscsiTgtAuthAttributesTable
  iscsiInitiator
    iscsiInitiatorAttributesTable
    iscsiInitiatorLoginStatsTable
      -- Counts successful and unsuccessful logins
    iscsiInitiatorLogoutStatsTable
      -- Counts normal and abnormal logouts
  iscsiIntrAuthorization
    iscsiIntrAuthAttributesTable
  iscsiSession
    iscsiSessionAttributesTable
    iscsiSessionStatsTable
      -- Performance-related counts (requests, responses, bytes)
    iscsiSessionCxnErrorStatsTable
      -- Counts digest errors, connection errors, etc.
  iscsiConnection
    iscsiConnectionAttributesTable

```

Note that this module does not attempt to count everything that could be counted; it is designed to include only those counters that would be useful for identifying performance, security, and fault problems from a management station.

### 6.3. iscsiInstance

The iscsiInstanceAttributesTable is the primary table of the iSCSI MIB module. Every table entry in this module is "owned" by exactly one iSCSI instance; all other table entries in the module include this table's index as their primary index.

Most implementations will include just one iSCSI instance row in this table. However, this table exists to allow for multiple virtual instances. For example, many IP routing products now allow multiple virtual routers. The iSCSI MIB module has the same premise; a large system could be "partitioned" into multiple, distinct virtual systems.

This also allows a single SNMP agent to proxy for multiple subsystems, perhaps a set of stackable devices, each of which has one or even more instances.

The instance attributes include the iSCSI vendor and version, as well as information on the last target or initiator at the other end of a session that caused a session failure.

The iscsiInstanceSsnErrorStatsTable augments the attributes table and provides statistics on session failures due to digest, connection, or iSCSI format errors.

### 6.4. iscsiPortal

The iscsiPortalAttributesTable lists iSCSI portals that can be used to listen for connections to targets, to initiate connections to other targets, or to do both.

Each row in the table includes an IP address (either v4 or v6), and a transport protocol (currently only TCP is defined). Each portal may have additional attributes, depending on whether it is an initiator portal, a target portal, or both. Initiator portals also have portal tags; these are placed in corresponding rows in the iscsiIntrPortalAttributesTable. Target portals have both portal tags and ports (e.g., TCP listen ports if the transport protocol is TCP); these are placed in rows in the iscsiTgtPortalAttributesTable.

Portal rows, along with their initiator and target portal counterparts, may be created and destroyed through this MIB module by a management station. Rows in the initiator and target portal tables are created and destroyed automatically by the agent when a row is created or destroyed in the `iscsiPortalAttributesTable` or when the value of `iscsiPortalRoles` changes. Attributes in these tables may then be modified by the management station if the agent implementation allows.

When created by a management station, the `iscsiPortalRoles` attribute is used to control row creation in the initiator and target portal tables. Creating a row with the `targetTypePortal` bit set in `iscsiPortalRoles` will cause the implementation to start listening for iSCSI connections on the portal. Creating a row with the `initiatorTypePortal` bit set in `iscsiPortalRoles` will not necessarily cause connections to be established; it is left to the implementation whether and when to make use of the portal. Both bits may be set if the portal is to be used by both initiator and target nodes.

When deleting a row in the `iscsiPortalAttributesTable`, all connections associated with that row are terminated. The implementation may either terminate the connection immediately or request a clean shutdown as specified in [RFC7143]. An outbound connection (when an `iscsiInitiatorPortal` is deleted) matches the portal if its `iscsiCxnLocalAddr` matches the `iscsiPortalAddr`. An inbound connection (when an `iscsiTargetPortal` is deleted) matches the portal if its `iscsiCxnLocalAddr` matches the `iscsiPortalAddr` and if its `iscsiCxnLocalPort` matches the `iscsiTargetPortalPort`.

Individual objects within a row in this table may not be modified while the row is active. For instance, changing the IP address of a portal requires that the rows associated with the old IP address be deleted and that new rows be created (in either order).

#### 6.5. `iscsiTargetPortal`

The `iscsiTgtPortalAttributesTable` contains target-specific attributes for iSCSI portals. Rows in this table use the same indices as their corresponding rows in the `iscsiPortalAttributesTable`, with the addition of `iscsiNodeIndex`.

Rows in this table are created when the `targetTypePortal` bit is set in the `iscsiPortalRoles` attribute of the corresponding `iscsiPortalAttributesEntry`; they are destroyed when this bit is cleared.

This table contains the TCP (or other protocol) port on which the socket is listening for incoming connections. It also includes a portal group aggregation tag; iSCSI target portals that are within this instance and share the same tag can contain connections within the same session.

This table will be empty for iSCSI instances that contain only initiators (such as iSCSI host driver implementations).

Many implementations use the same Target Portal Group Tag and protocol port for all nodes accessed via a portal. These implementations will create a single row in the `iscsitGtPortalAttributeTable`, with an `iscsiNodeIndex` of zero.

Other implementations do not use the same tag and/or port for all nodes; these implementations will create a row in this table for each (portal, node) tuple, using `iscsiNodeIndex` to designate the node for this portal tag and port.

#### 6.6. `iscsiInitiatorPortal`

The `iscsiIntrPortalAttributesTable` contains initiator-specific objects for iSCSI portals. Rows in this table use the same indices as their corresponding entries in the `iscsiPortalAttributesTable`. A row in this table is created when the `initiatorTypePortal` bit is set in the `iscsiPortalRoles` attribute; it is destroyed when this bit is cleared.

Each row in this table contains a portal group aggregation tag, indicating which portals an initiator may use together within a multiple-connection session.

This table will be empty for iSCSI instances that contain only targets (such as most iSCSI devices).

Many implementations use the same initiator tag for all nodes accessing targets via a given portal. These implementations will create a single row in `iscsiIntrPortalAttributeTable`, with an `iscsiNodeIndex` of zero.

Other implementations do not use the same tag and/or port for all nodes; these implementations will create a row in this table for each (portal, node) tuple, using `iscsiNodeIndex` to designate the node for this portal tag and port.

### 6.7. iscsiNode

The iscsiNodeAttributesTable contains a list of iSCSI nodes, each of which may have an initiator role, a target role, or both.

This table contains the node's attributes that are common to both roles, such as its iSCSI name and alias string. Attributes specific to initiators or targets are available in the iscsiTarget and iscsiInitiator objects. Each row in this table that can fulfill a target role has a corresponding row in the iscsiTarget table; each entry that fulfills an initiator role has a row in the iscsiInitiator table. Nodes such as copy managers that can take on both roles have a corresponding row in each table.

This table also contains the login negotiations preferences for this node. These objects indicate the values this node will offer or prefer in the operational negotiation phase of the login process.

For most implementations, each entry in the table also contains a RowPointer to the transport table entry in the SCSI MIB module that this iSCSI node represents. For implementations without a standard SCSI layer above iSCSI, such as an iSCSI proxy or gateway, this RowPointer can point to a row in an implementation-specific table that this iSCSI node represents.

### 6.8. iscsiTarget

The iscsiTargetAttributesTable contains target-specific attributes for iSCSI nodes. Each entry in this table uses the same index values as its corresponding iscsiNode entry.

This table contains attributes used to indicate the last failure that was (or should have been) sent as a notification.

This table is augmented by the iscsiTargetLoginStatsTable and the iscsiTargetLogoutStatsTable, which count the numbers of normal and abnormal logins and logouts to this target.

### 6.9. iscsiTgtAuthorization

The iscsiTgtAuthAttributesTable contains an entry for each initiator identifier that will be allowed to access the target under which it appears. Each entry contains a RowPointer to a user identity in the IPS Authorization MIB module, which contains the name, address, and credential information necessary to authenticate the initiator.

### 6.10. iscsiInitiator

The iscsiInitiatorAttributesTable contains a list of initiator-specific attributes for iSCSI nodes. Each entry in this table uses the same index values as its corresponding iscsiNode entry.

Most implementations will include a single entry in this table, regardless of the number of physical interfaces the initiator may use.

This table is augmented by the iscsiInitiatorLoginStatsTable and the iscsiInitiatorLogoutStatsTable, which count the numbers of normal and abnormal logins and logouts from this initiator.

### 6.11. iscsiIntrAuthorization

The iscsiIntrAuthAttributesTable contains an entry for each target identifier to which the initiator is configured to establish a session.

Each entry contains a RowPointer to a user identity in the IPS Authorization MIB module, which contains the name, address, and credential information necessary to identify (for discovery purposes) and authenticate the target.

### 6.12. iscsiSession

The iscsiSessionAttributesTable contains a set of rows that list the sessions known to exist locally for each node in each iSCSI instance.

The session type for each session indicates whether the session is used for normal SCSI commands or for discovery using the SendTargets text command. Discovery sessions that do not belong to any particular node have a node index attribute of zero.

The session direction for each session indicates whether it is an Inbound session or an Outbound session. Inbound sessions are from some other initiator to the target node under which the session appears. Outbound sessions are from the initiator node under which the session appears to a target outside this iSCSI instance.

Many attributes may be negotiated when starting an iSCSI session. Most of these attributes are included in the session object.

Some attributes, such as the integrity and authentication schemes, have some standard values that can be extended by vendors to include their own schemes. These contain an object identifier, rather than the expected enumerated type, to allow these values to be extended by other MIB modules, such as an enterprise MIB module.

The `iscsiSessionStatsTable` includes statistics related to performance; it counts iSCSI data bytes and PDUs.

For implementations that support error recovery without terminating a session, the `iscsiSessionCxnErrorStatsTable` contains counters for the numbers of digest and connection errors that have occurred within the session.

#### 6.13. `iscsiConnection`

The `iscsiConnectionAttributesTable` contains a list of active connections within each session. It contains the IP addresses and TCP (or other protocol) ports of both the local and remote sides of the connection. These may be used to locate other connection-related information and statistics in the TCP MIB module [RFC4022].

The attributes table also contains a connection state. This state is not meant to directly map to the state tables included within the iSCSI specification; they are meant to be simplified, higher-level definitions of connection state that provide information more useful to a user or network manager.

No statistics are kept for connections.

#### 6.14. IP Addresses and TCP Port Numbers

The IP addresses in this module are represented by two attributes, one of type `InetAddressType`, and the other of type `InetAddress`. These are taken from [RFC4001], which specifies how to support addresses that may be either IPv4 or IPv6.

The TCP port numbers that appear in a few of the structures are described as simply port numbers, with a protocol attribute indicating whether they are TCP ports or something else. This will allow the module to be compatible with iSCSI over transports other than TCP in the future.

### 6.15. Descriptors: Using OIDs in Place of Enumerated Types

The iSCSI MIB module has a few attributes, namely, the digest method attributes, where an enumerated type would work well, except that an implementation may need to extend the attribute and add types of its own. To make this work, this MIB module defines a set of object identities within the `iscsiDescriptors` subtree. Each of these object identities is basically an enumerated type.

Attributes that make use of these object identities have a value that is an Object Identifier (OID) instead of an enumerated type. These OIDs can indicate either the object identities defined in this module or object identities defined elsewhere, such as in an enterprise MIB module. Those implementations that add their own digest methods should also define a corresponding object identity for each of these methods within their own enterprise MIB module, and return its OID whenever one of these attributes is using that method.

### 6.16. Notifications

Three notifications are provided. One is sent by an initiator detecting a critical login failure, another is sent by a target detecting a critical login failure, and the third is sent upon a session being terminated due to an abnormal connection or digest failure. Critical failures are defined as those that may expose security-related problems that may require immediate action, such as failures due to authentication, authorization, or negotiation problems. Attributes in the initiator, target, and instance objects provide the information necessary to send in the notification, such as the initiator or target name and IP address at the other end that may have caused the failure.

To avoid sending an excessive number of notifications due to multiple errors counted, an SNMP agent implementing the iSCSI MIB module **SHOULD NOT** send more than three iSCSI notifications in any 10-second period.

The 3-in-10 rule was chosen because one notification every three seconds was deemed often enough, but should two or three different notifications happen at the same time, it would not be desirable to suppress them. Three notifications in 10 seconds is a happy medium, where a short burst of notifications is allowed, without inundating the network and/or notification host with a large number of notifications.

## 7. MIB Definition

```
ISCSI-MIB DEFINITIONS ::= BEGIN

IMPORTS
MODULE-IDENTITY, OBJECT-TYPE, OBJECT-IDENTITY, NOTIFICATION-TYPE,
Unsigned32, Counter32, Counter64, Gauge32,
mib-2
FROM SNMPv2-SMI

TEXTUAL-CONVENTION, TruthValue, RowPointer, TimeStamp, RowStatus,
AutonomousType, StorageType
FROM SNMPv2-TC

MODULE-COMPLIANCE, OBJECT-GROUP, NOTIFICATION-GROUP
FROM SNMPv2-CONF

SnmpAdminString
FROM SNMP-FRAMEWORK-MIB -- RFC 3411

InetAddressType, InetAddress, InetPortNumber
FROM INET-ADDRESS-MIB -- RFC 4001
;

iscsiMibModule MODULE-IDENTITY
LAST-UPDATED "201402180000Z" -- February 18, 2014
ORGANIZATION "IETF STORage Maintenance (STORM) Working Group"

CONTACT-INFO "
Working Group Email: storm@ietf.org
Attn: Mark Bakke
Dell
Email: mark_bakke@dell.com

Prakash Venkatesen
HCL Technologies
Email: prakashvn@hcl.com"

DESCRIPTION
"This module defines management information specific
to the iSCSI protocol.

Copyright (c) 2014 IETF Trust and the persons identified as
authors of the code. All rights reserved.

Redistribution and use in source and binary forms, with or
without modification, is permitted pursuant to, and subject
to the license terms contained in, the Simplified BSD
```

License set forth in Section 4.c of the IETF Trust's Legal Provisions Relating to IETF Documents (<http://trustee.ietf.org/license-info>)."

REVISION "201402180000Z"

DESCRIPTION

"Second version of the iSCSI Protocol MIB Module. RFC 7143 makes several updates to [RFC3720]. This version makes corresponding updates to the MIB module. This MIB module published as RFC 7147."

REVISION "200605220000Z"

DESCRIPTION

"Initial version of the iSCSI Protocol MIB module. This MIB module published as RFC 4544."

`::= { mib-2 142 }`

iscsciNotifications OBJECT IDENTIFIER ::= { iscsiMibModule 0 }

iscsciObjects OBJECT IDENTIFIER ::= { iscsiMibModule 1 }

iscsciConformance OBJECT IDENTIFIER ::= { iscsiMibModule 2 }

iscsciAdmin OBJECT IDENTIFIER ::= { iscsiMibModule 3 }

-- Textual Conventions

IscsiTransportProtocol ::= TEXTUAL-CONVENTION

DISPLAY-HINT "d"

STATUS current

DESCRIPTION

"This data type is used to define the transport protocols that will carry iSCSI PDUs. Protocol numbers are assigned by IANA. A current list of all assignments is available from <<http://www.iana.org/assignments/protocol-numbers/>>."

SYNTAX Unsigned32 (0..255)

IscsiDigestMethod ::= TEXTUAL-CONVENTION

STATUS current

DESCRIPTION

"This data type represents the methods possible for digest negotiation.

- none - a placeholder for a secondary digest method that means only the primary method can be used.
- other - a digest method other than those defined below.
- noDigest - does not support digests (will operate without a digest (Note: implementations must support digests to be compliant with RFC 7143)).
- CRC32C - require a CRC32C digest."

## REFERENCE

"RFC 7143, Section 13.1, HeaderDigest and DataDigest"

SYNTAX            INTEGER {  
                   none(1),  
                   other(2),  
                   noDigest(3),  
                   crc32c(4)  
                   }

**IscsiName ::= TEXTUAL-CONVENTION**

DISPLAY-HINT "223t"

STATUS        current

## DESCRIPTION

"This data type is used for objects whose value is an iSCSI name with the properties described in RFC 7143, Section 4.2.7.1, and encoded as specified in RFC 7143, Section 4.2.7.2. A zero-length string indicates the absence of an iSCSI name."

## REFERENCE

"RFC 7143, Section 4.2.7, iSCSI Names."

SYNTAX        OCTET STRING (SIZE(0 | 16..223))

--\*\*\*\*\*

**iscsiDescriptors OBJECT IDENTIFIER ::= { iscsiAdmin 1 }**

**iscsiHeaderIntegrityTypes OBJECT IDENTIFIER ::= { iscsiDescriptors 1 }**

**iscsiHdrIntegrityNone OBJECT-IDENTITY**

STATUS        current

## DESCRIPTION

"The authoritative identifier when no integrity scheme for the header is being used."

## REFERENCE

"RFC 7143, Section 13.1, HeaderDigest and DataDigest"

::= { iscsiHeaderIntegrityTypes 1 }

**iscsiHdrIntegrityCrc32c OBJECT-IDENTITY**

STATUS        current

## DESCRIPTION

"The authoritative identifier when the integrity scheme for the header is CRC32c."

## REFERENCE

"RFC 7143, Section 13.1, HeaderDigest and DataDigest"

::= { iscsiHeaderIntegrityTypes 2 }

**iscsiDataIntegrityTypes OBJECT IDENTIFIER ::= { iscsiDescriptors 2 }**

```

iscsiDataIntegrityNone OBJECT-IDENTITY
  STATUS      current
  DESCRIPTION
    "The authoritative identifier when no integrity
     scheme for the data is being used."
  REFERENCE
    "RFC 7143, Section 13.1, HeaderDigest and DataDigest"
 ::= { iscsiDataIntegrityTypes 1 }

iscsiDataIntegrityCrc32c OBJECT-IDENTITY
  STATUS      current
  DESCRIPTION
    "The authoritative identifier when the integrity
     scheme for the data is CRC32c."
  REFERENCE
    "RFC 7143, Section 13.1, HeaderDigest and DataDigest"
 ::= { iscsiDataIntegrityTypes 2 }

--*****  

iscsiInstance OBJECT IDENTIFIER ::= { iscsiObjects 1 }

-- Instance Attributes Table

iscsiInstanceAttributesTable OBJECT-TYPE
  SYNTAX      SEQUENCE OF IscsiInstanceAttributesEntry
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "A list of iSCSI instances present on the system."
 ::= { iscsiInstance 1 }

iscsiInstanceAttributesEntry OBJECT-TYPE
  SYNTAX      IscsiInstanceAttributesEntry
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "An entry (row) containing management information applicable
     to a particular iSCSI instance."
  INDEX { iscsiInstIndex }
 ::= { iscsiInstanceAttributesTable 1 }

IscsiInstanceAttributesEntry ::= SEQUENCE {
  iscsiInstIndex          Unsigned32,
  iscsiInstDescr           SnmpAdminString,
  iscsiInstVersionMin     Unsigned32,
  iscsiInstVersionMax     Unsigned32,
  iscsiInstVendorID        SnmpAdminString,
}

```

```

iscsiInstVendorVersion      SnmpAdminString,
iscsiInstPortalNumber      Unsigned32,
iscsiInstNodeNumber        Unsigned32,
iscsiInstSessionNumber     Unsigned32,
iscsiInstSsnFailures      Counter32,
iscsiInstLastSsnFailureType AutonomousType,
iscsiInstLastSsnRmtNodeName IscsiName,
iscsiInstDiscontinuityTime TimeStamp,
iscsiInstXNodeArchitecture SnmpAdminString
}

iscsiInstIndex OBJECT-TYPE
  SYNTAX      Unsigned32 (1..4294967295)
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "An arbitrary integer used to uniquely identify a particular
     iSCSI instance. This index value must not be modified or
     reused by an agent unless a reboot has occurred. An agent
     should attempt to keep this value persistent across reboots."
 ::= { iscsiInstanceAttributesEntry 1 }

iscsiInstDescr OBJECT-TYPE
  SYNTAX      SnmpAdminString
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "A UTF-8 string, determined by the implementation to
     describe the iSCSI instance. When only a single instance
     is present, this object may be set to the zero-length
     string; with multiple iSCSI instances, it may be used in
     an implementation-dependent manner to describe the purpose
     of the respective instance."
 ::= { iscsiInstanceAttributesEntry 2 }

iscsiInstVersionMin OBJECT-TYPE
  SYNTAX      Unsigned32 (0..255)
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The minimum version number of the iSCSI specification
     such that this iSCSI instance supports this minimum
     value, the maximum value indicated by the corresponding
     instance in iscsiInstVersionMax, and all versions in
     between."
  REFERENCE
    "RFC 7143, Section 11.12, Login Request"

```

```

 ::= { iscsiInstanceAttributesEntry 3 }

iscsiInstVersionMax OBJECT-TYPE
    SYNTAX      Unsigned32 (0..255)
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The maximum version number of the iSCSI specification
         such that this iSCSI instance supports this maximum
         value, the minimum value indicated by the corresponding
         instance in iscsiInstVersionMin, and all versions in
         between."
    REFERENCE
        "RFC 7143, Section 11.12, Login Request"
 ::= { iscsiInstanceAttributesEntry 4 }

iscsiInstVendorID OBJECT-TYPE
    SYNTAX      SnmpAdminString
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "A UTF-8 string describing the manufacturer of the
         implementation of this instance."
 ::= { iscsiInstanceAttributesEntry 5 }

iscsiInstVendorVersion OBJECT-TYPE
    SYNTAX      SnmpAdminString
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "A UTF-8 string set by the manufacturer describing the
         version of the implementation of this instance. The
         format of this string is determined solely by the
         manufacturer; the string is for informational purposes only.
         It is unrelated to the iSCSI specification version numbers."
 ::= { iscsiInstanceAttributesEntry 6 }

iscsiInstPortalNumber OBJECT-TYPE
    SYNTAX      Unsigned32
    UNITS      "transport endpoints"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The number of rows in the iscsiPortalAttributesTable
         that are currently associated with this iSCSI instance."
 ::= { iscsiInstanceAttributesEntry 7 }

iscsiInstNodeNumber OBJECT-TYPE

```

```

SYNTAX      Unsigned32
UNITS      "iSCSI nodes"
MAX-ACCESS  read-only
STATUS     current
DESCRIPTION
    "The number of rows in the iscsiNodeAttributesTable
     that are currently associated with this iSCSI instance."
 ::= { iscsiInstanceAttributesEntry 8 }

iscsiInstSessionNumber OBJECT-TYPE
    SYNTAX      Unsigned32
    UNITS      "sessions"
    MAX-ACCESS  read-only
    STATUS     current
    DESCRIPTION
        "The number of rows in the iscsiSessionAttributesTable
         that are currently associated with this iSCSI instance."
 ::= { iscsiInstanceAttributesEntry 9 }

iscsiInstSsnFailures OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "sessions"
    MAX-ACCESS  read-only
    STATUS     current
    DESCRIPTION
        "This object counts the number of times a session belonging
         to this instance has failed. If this counter has
         suffered a discontinuity, the time of the last discontinuity
         is indicated in iscsiInstDiscontinuityTime."
    REFERENCE
        "RFC 7143, Section 13.1, HeaderDigest and DataDigest"
 ::= { iscsiInstanceAttributesEntry 10 }

iscsiInstLastSsnFailureType OBJECT-TYPE
    SYNTAX      AutonomousType
    MAX-ACCESS  read-only
    STATUS     current
    DESCRIPTION
        "The counter object in the iscsiInstanceSsnErrorStatsTable
         that was incremented when the last session failure occurred.

         If the reason for failure is not found in the
         iscsiInstanceSsnErrorStatsTable, the value { 0.0 } is
         used instead."
 ::= { iscsiInstanceAttributesEntry 11 }

iscsiInstLastSsnRmtNodeName OBJECT-TYPE
    SYNTAX      IscsiName

```

```

MAX-ACCESS    read-only
STATUS        current
DESCRIPTION
  "The iSCSI name of the remote node from the failed
  session."
 ::= { iscsiInstanceAttributesEntry 12 }

iscsiInstDiscontinuityTime OBJECT-TYPE
  SYNTAX        TimeStamp
  MAX-ACCESS    read-only
  STATUS        current
  DESCRIPTION
    "The value of SysUpTime on the most recent occasion
     at which any one or more of this instance's counters
     suffered a discontinuity.

    If no such discontinuities have occurred since the last
    re-initialization of the local management subsystem,
    then this object contains a zero value."
 ::= { iscsiInstanceAttributesEntry 13 }

iscsiInstXNodeArchitecture OBJECT-TYPE
  SYNTAX        SnmpAdminString
  MAX-ACCESS    read-only
  STATUS        current
  DESCRIPTION
    "A UTF-8 string set by the manufacturer declaring the
     details of its iSCSI node architecture to the remote
     endpoint. These details may include, but are not limited
     to, iSCSI vendor software, firmware, or hardware versions,
     the OS version, or hardware architecture.
     The format of this string is determined solely by the
     manufacturer; the string is for informational purposes only.
     It is unrelated to the iSCSI specification version numbers."
  REFERENCE
    "RFC 7143, Section 13.26, X#NodeArchitecture"
 ::= { iscsiInstanceAttributesEntry 14 }

-- Instance Session Failure Stats Table

iscsiInstanceSsnErrorStatsTable OBJECT-TYPE
  SYNTAX        SEQUENCE OF IscsiInstanceSsnErrorStatsEntry
  MAX-ACCESS    not-accessible
  STATUS        current
  DESCRIPTION
    "Statistics regarding the occurrences of error types
     that result in a session failure."
 ::= { iscsiInstance 2 }

```

```

iscsiInstanceSsnErrorStatsEntry OBJECT-TYPE
  SYNTAX      IscsiInstanceSsnErrorStatsEntry
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "An entry (row) containing management information applicable
     to a particular iSCSI instance."
  AUGMENTS { iscsiInstanceAttributesEntry }
 ::= { iscsiInstanceSsnErrorStatsTable 1 }

IscsiInstanceSsnErrorStatsEntry ::= SEQUENCE {
  iscsiInstSsnDigestErrors      Counter32,
  iscsiInstSsnCxnTimeoutErrors  Counter32,
  iscsiInstSsnFormatErrors      Counter32,
  iscsiInstSsnTgtUnmappedErrors Counter32
}

iscsiInstSsnDigestErrors OBJECT-TYPE
  SYNTAX      Counter32
  UNITS      "sessions"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The count of sessions that failed due to receipt of
     a PDU containing header or data digest errors. If this
     counter has suffered a discontinuity, the time of the last
     discontinuity is indicated in iscsiInstDiscontinuityTime."
  REFERENCE
    "RFC 7143, Section 7.8, Digest Errors"
 ::= { iscsiInstanceSsnErrorStatsEntry 1 }

iscsiInstSsnCxnTimeoutErrors OBJECT-TYPE
  SYNTAX      Counter32
  UNITS      "sessions"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The count of sessions that failed due to a sequence
     exceeding a time limit. If this counter has suffered a
     discontinuity, the time of the last discontinuity
     is indicated in iscsiInstDiscontinuityTime."
  REFERENCE
    "RFC 7143, Section 7.5, Connection Timeout Management"
 ::= { iscsiInstanceSsnErrorStatsEntry 2 }

iscsiInstSsnFormatErrors OBJECT-TYPE
  SYNTAX      Counter32
  UNITS      "sessions"

```

```

MAX-ACCESS      read-only
STATUS         current
DESCRIPTION
    "The count of sessions that failed due to receipt of
     a PDU that contained a format error. If this counter has
     suffered a discontinuity, the time of the last discontinuity
     is indicated in iscsiInstDiscontinuityTime."
REFERENCE
    "RFC 7143 Section 7.7, Format Errors"
::= { iscsiInstanceSsnErrorStatsEntry 3 }

iscsiInstSsnTgtUnmappedErrors OBJECT-TYPE
    SYNTAX          Counter32
    UNITS           "sessions"
    MAX-ACCESS     read-only
    STATUS          current
    DESCRIPTION
        "The count of sessions that failed due to the target
         becoming unmapped. If this counter has
         suffered a discontinuity, the time of the last discontinuity
         is indicated in iscsiInstDiscontinuityTime."
::= { iscsiInstanceSsnErrorStatsEntry 4 }
--*****
```

```

iscsiPortal OBJECT IDENTIFIER ::= { iscsiObjects 2 }

-- Portal Attributes Table

iscsiPortalAttributesTable OBJECT-TYPE
    SYNTAX          SEQUENCE OF IscsiPortalAttributesEntry
    MAX-ACCESS     not-accessible
    STATUS          current
    DESCRIPTION
        "A list of transport endpoints (using TCP or another transport
         protocol) used by this iSCSI instance. An iSCSI instance may
         use a portal to listen for incoming connections to its targets,
         to initiate connections to other targets, or both."
::= { iscsiPortal 1 }

iscsiPortalAttributesEntry OBJECT-TYPE
    SYNTAX          IscsiPortalAttributesEntry
    MAX-ACCESS     not-accessible
    STATUS          current
    DESCRIPTION
        "An entry (row) containing management information applicable
         to a particular portal instance."
INDEX { iscsiInstIndex, iscsiPortalIndex  }
::= { iscsiPortalAttributesTable 1 }
```

```

IscsiPortalAttributesEntry ::= SEQUENCE {
    iscsiPortalIndex                  Unsigned32,
    iscsiPortalRowStatus               RowStatus,
    iscsiPortalRoles                  BITS,
    iscsiPortalAddrType               InetAddressType,
    iscsiPortalAddr                  InetAddress,
    iscsiPortalProtocol               IscsiTransportProtocol,
    iscsiPortalMaxRecvDataSegLength  Unsigned32,
    iscsiPortalPrimaryHdrDigest      IscsiDigestMethod,
    iscsiPortalPrimaryDataDigest     IscsiDigestMethod,
    iscsiPortalSecondaryHdrDigest   IscsiDigestMethod,
    iscsiPortalSecondaryDataDigest  IscsiDigestMethod,
    iscsiPortalRecvMarker            TruthValue,
    iscsiPortalStorageType           StorageType,
    iscsiPortalDescr                 SnmpAdminString
}

iscsiPortalIndex OBJECT-TYPE
    SYNTAX      Unsigned32 (1..4294967295)
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "An arbitrary integer used to uniquely identify a particular
         transport endpoint within this iSCSI instance. This index
         value must not be modified or reused by an agent unless a
         reboot has occurred. An agent should attempt to keep this
         value persistent across reboots."
::= { iscsiPortalAttributesEntry 1 }

iscsiPortalRowStatus OBJECT-TYPE
    SYNTAX      RowStatus
    MAX-ACCESS  read-create
    STATUS      current
    DESCRIPTION
        "This field allows entries to be dynamically added and
         removed from this table via SNMP. When adding a row to
         this table, all non-Index/RowStatus objects must be set.
         When the value of this object is 'active', the values of
         the other objects in this table cannot be changed.
         Rows may be discarded using RowStatus.

        Note that creating a row in this table will typically
        cause the agent to create one or more rows in the
        iscsiTgtPortalAttributesTable and/or the
        iscsiIntrPortalAttributesTable."
::= { iscsiPortalAttributesEntry 2 }

iscsiPortalRoles OBJECT-TYPE

```

```

SYNTAX      BITS {
            targetTypePortal(0),
            initiatorTypePortal(1)
        }
MAX-ACCESS  read-create
STATUS      current
DESCRIPTION
    "A portal can operate in one or both of two roles:
     as a target portal and/or an initiator portal.  If
     the portal will operate in both roles, both bits
     must be set.

This object will define a corresponding row that
will exist or must be created in the
iscsiTgtPortalAttributesTable, the
iscsiIntrPortalAttributesTable, or both.  If the
targetTypePortal bit is set, one or more corresponding
iscsiTgtPortalAttributesEntry rows will be found or
created.  If the initiatorTypePortal bit is set,
one or more corresponding iscsiIntrPortalAttributesEntry
rows will be found or created.  If both bits are set, one
or more corresponding rows will be found or created in
one of the above tables."
 ::= { iscsiPortalAttributesEntry 3 }

iscsiPortalAddrType OBJECT-TYPE
SYNTAX      InetAddressType
MAX-ACCESS  read-create
STATUS      current
DESCRIPTION
    "The type of Internet Network Address contained in the
     corresponding instance of the iscsiPortalAddr."
DEFVAL      { ipv4 }
 ::= { iscsiPortalAttributesEntry 4 }

iscsiPortalAddr OBJECT-TYPE
SYNTAX      InetAddress
MAX-ACCESS  read-create
STATUS      current
DESCRIPTION
    "The portal's Internet Network Address, of the type
     specified by the object iscsiPortalAddrType.  If
     iscsiPortalAddrType has the value 'dns', this address
     gets resolved to an IP address whenever a new iSCSI
     connection is established using this portal."
 ::= { iscsiPortalAttributesEntry 5 }

iscsiPortalProtocol OBJECT-TYPE

```

```

SYNTAX          IscsiTransportProtocol
MAX-ACCESS     read-create
STATUS         current
DESCRIPTION
    "The portal's transport protocol."
DEFVAL         { 6 } -- TCP
 ::= { iscsiPortalAttributesEntry 6 }

iscsiPortalMaxRecvDataSegLength OBJECT-TYPE
SYNTAX          Unsigned32 (512..16777215)
UNITS           "bytes"
MAX-ACCESS     read-create
STATUS         current
DESCRIPTION
    "The maximum PDU length this portal can receive.
    This may be constrained by hardware characteristics,
    and individual implementations may choose not to
    allow this object to be changed."
REFERENCE
    "RFC 7143, Section 13.12, MaxRecvDataSegmentLength"
DEFVAL         { 8192 }
 ::= { iscsiPortalAttributesEntry 7 }

iscsiPortalPrimaryHdrDigest OBJECT-TYPE
SYNTAX          IscsiDigestMethod
MAX-ACCESS     read-create
STATUS         current
DESCRIPTION
    "The preferred header digest for this portal."
DEFVAL         { crc32c }
 ::= { iscsiPortalAttributesEntry 8 }

iscsiPortalPrimaryDataDigest OBJECT-TYPE
SYNTAX          IscsiDigestMethod
MAX-ACCESS     read-create
STATUS         current
DESCRIPTION
    "The preferred data digest method for this portal."
DEFVAL         { crc32c }
 ::= { iscsiPortalAttributesEntry 9 }

iscsiPortalSecondaryHdrDigest OBJECT-TYPE
SYNTAX          IscsiDigestMethod
MAX-ACCESS     read-create
STATUS         current
DESCRIPTION
    "An alternate header digest preference for this portal."
DEFVAL         { noDigest }

```

```

 ::= { iscsiPortalAttributesEntry 10 }

iscsiPortalSecondaryDataDigest OBJECT-TYPE
    SYNTAX      IscsiDigestMethod
    MAX-ACCESS  read-create
    STATUS      current
    DESCRIPTION
        "An alternate data digest preference for this portal."
    DEFVAL      { noDigest }
 ::= { iscsiPortalAttributesEntry 11 }

iscsiPortalRecvMarker OBJECT-TYPE
    SYNTAX      TruthValue
    MAX-ACCESS  read-create
    STATUS      deprecated
    DESCRIPTION
        "This object indicates whether or not this portal will
         request markers in its incoming data stream."
    REFERENCE
        "RFC 7143, Section 13.25, Obsoleted Keys."
    DEFVAL      { false }
 ::= { iscsiPortalAttributesEntry 12 }

iscsiPortalStorageType OBJECT-TYPE
    SYNTAX      StorageType
    MAX-ACCESS  read-create
    STATUS      current
    DESCRIPTION
        "The storage type for this row. Rows in this table that were
         created through an external process (e.g., not created via
         this MIB) may have a storage type of readOnly or permanent.

         Conceptual rows having the value 'permanent' need not
         allow write access to any columnar objects in the row."
    DEFVAL      { nonVolatile }
 ::= { iscsiPortalAttributesEntry 13 }

iscsiPortalDescr OBJECT-TYPE
    SYNTAX      SnmpAdminString
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "A UTF-8 string, determined by the implementation to
         describe the iSCSI portal. When only a single instance
         is present, this object may be set to the zero-length
         string; with multiple iSCSI portals, it may be used in
         an implementation-dependent manner to describe the
         respective portal, and could include information such as

```

```

    Host Bus Adapter (HBA) model, description, and version, or
    software driver and version."
 ::= { iscsiPortalAttributesEntry 14 }

--*****iscsiTargetPortal OBJECT IDENTIFIER ::= { iscsiObjects 3 }

-- Target Portal Attributes Table

iscsiTgtPortalAttributesTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF IscsiTgtPortalAttributesEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "A list of transport endpoints (using TCP or another transport
         protocol) on which this iSCSI instance listens for incoming
         connections to its targets."
 ::= { iscsiTargetPortal 1 }

iscsiTgtPortalAttributesEntry OBJECT-TYPE
    SYNTAX      IscsiTgtPortalAttributesEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "An entry (row) containing management information applicable
         to a particular portal instance that is used to listen for
         incoming connections to local targets. One or more rows in
         this table is populated by the agent for each
         iscsiPortalAttributesEntry row that has the bit
         targetTypePortal set in its iscsiPortalRoles column."
    INDEX { iscsiInstIndex, iscsiPortalIndex,
            iscsiTgtPortalNodeIndexOrZero }
 ::= { iscsiTgtPortalAttributesTable 1 }

IscsiTgtPortalAttributesEntry ::= SEQUENCE {
    iscsiTgtPortalNodeIndexOrZero  Unsigned32,
    iscsiTgtPortalPort           InetPortNumber,
    iscsiTgtPortalTag            Unsigned32
}

iscsiTgtPortalNodeIndexOrZero OBJECT-TYPE
    SYNTAX      Unsigned32 (0..4294967295)
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "An arbitrary integer used to uniquely identify a
         particular node within an iSCSI instance present
         on the local system.

```

For implementations where each {portal, node} tuple can have a different portal tag, this value will map to the iscsiNodeIndex.

For implementations where the portal tag is the same for a given portal regardless of which node is using the portal, the value 0 (zero) is used."

```
::= { iscsiTgtPortalAttributesEntry 1 }
```

**iscsiTgtPortalPort** OBJECT-TYPE

SYNTAX InetPortNumber (1..65535)

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The portal's transport protocol port number on which the portal listens for incoming iSCSI connections when the portal is used as a target portal. This object's storage type is specified in iscsiPortalStorageType."

```
::= { iscsiTgtPortalAttributesEntry 2 }
```

**iscsiTgtPortalTag** OBJECT-TYPE

SYNTAX Unsigned32 (1..65535)

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The portal's aggregation tag when the portal is used as a target portal. Multiple-connection sessions may be aggregated over portals sharing an identical aggregation tag. This object's storage type is specified in iscsiPortalStorageType."

REFERENCE

"RFC 7143, Section 4.4.1, iSCSI Architecture Model"

```
::= { iscsiTgtPortalAttributesEntry 3 }
```

---

**iscsiInitiatorPortal** OBJECT IDENTIFIER ::= { iscsiObjects 4 }

-- Initiator Portal Attributes Table

**iscsiIntrPortalAttributesTable** OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiIntrPortalAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A list of Internet Network Addresses (using TCP or another transport protocol) from which this iSCSI instance may initiate connections to other targets."

```

 ::= { iscsiInitiatorPortal 1 }

iscsiIntrPortalAttributesEntry OBJECT-TYPE
    SYNTAX      IscsiIntrPortalAttributesEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "An entry (row) containing management information applicable
         to a particular portal instance that is used to initiate
         connections to iSCSI targets. One or more rows in
         this table is populated by the agent for each
         iscsiPortalAttributesEntry row that has the bit
         initiatorTypePortal set in its iscsiPortalRoles column."
    INDEX { iscsiInstIndex, iscsiPortalIndex,
            iscsiIntrPortalNodeIndexOrZero  }
 ::= { iscsiIntrPortalAttributesTable 1 }

IscsiIntrPortalAttributesEntry ::= SEQUENCE {
    iscsiIntrPortalNodeIndexOrZero Unsigned32,
    iscsiIntrPortalTag           Unsigned32
}

iscsiIntrPortalNodeIndexOrZero OBJECT-TYPE
    SYNTAX      Unsigned32 (0..4294967295)
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "An arbitrary integer used to uniquely identify a
         particular node within an iSCSI instance present
         on the local system.

For implementations where each {portal, node} tuple
can have a different portal tag, this value will
map to the iscsiNodeIndex.

For implementations where the portal tag is the
same for a given portal regardless of which node
is using the portal, the value 0 (zero) is used."
 ::= { iscsiIntrPortalAttributesEntry 1 }

iscsiIntrPortalTag OBJECT-TYPE
    SYNTAX      Unsigned32 (1..65535)
    MAX-ACCESS  read-write
    STATUS      current
    DESCRIPTION
        "The portal's aggregation tag when the portal is used as
         an initiator portal. Multiple-connection sessions may
         be aggregated over portals sharing an identical

```

```

aggregation tag. This object's storage type is
specified in iscsiPortalStorageType."
```

**REFERENCE**

```
"RFC 7143, Section 4.4.1, iSCSI Architecture Model"
```

```
::= { iscsiIntrPortalAttributesEntry 2 }
```

---

```
iscsiNode OBJECT IDENTIFIER ::= { iscsiObjects 5 }
```

-- Node Attributes Table

```
iscsiNodeAttributesTable OBJECT-TYPE
  SYNTAX      SEQUENCE OF IscsiNodeAttributesEntry
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "A list of iSCSI nodes belonging to each iSCSI instance
     present on the local system. An iSCSI node can act as
     an initiator, a target, or both."
 ::= { iscsiNode 1 }
```

```
iscsiNodeAttributesEntry OBJECT-TYPE
  SYNTAX      IscsiNodeAttributesEntry
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "A conceptual row containing management information
     applicable to a particular iSCSI node."
  INDEX { iscsiInstIndex, iscsiNodeIndex }
 ::= { iscsiNodeAttributesTable 1 }
```

```
IscsiNodeAttributesEntry ::= SEQUENCE {
  iscsiNodeIndex                  Unsigned32,
  iscsinodeName                   IscsiName,
  iscsiNodeAlias                  SnmpAdminString,
  iscsiNodeRoles                  BITS,
  iscsiNodeTransportType          RowPointer,
  iscsiNodeInitialR2T             TruthValue,
  iscsiNodeImmediateData          TruthValue,
  iscsiNodeMaxOutstandingR2T     Unsigned32,
  iscsiNodeFirstBurstLength       Unsigned32,
  iscsiNodeMaxBurstLength         Unsigned32,
  iscsiNodeMaxConnections         Unsigned32,
  iscsiNodeDataSequenceInOrder    TruthValue,
  iscsiNodeDataPDUInOrder         TruthValue,
  iscsiNodeDefaultTime2Wait      Unsigned32,
  iscsiNodeDefaultTime2Retain     Unsigned32,
```

```

iscsiNodeErrorRecoveryLevel      Unsigned32,
iscsiNodeDiscontinuityTime       TimeStamp,
iscsiNodeStorageType             StorageType
}

iscsiNodeIndex OBJECT-TYPE
  SYNTAX      Unsigned32 (1..4294967295)
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "An arbitrary integer used to uniquely identify a particular
     node within an iSCSI instance. This index value must not be
     modified or reused by an agent unless a reboot has occurred.
     An agent should attempt to keep this value persistent across
     reboots."
 ::= { iscsiNodeAttributesEntry 1 }

iscsiNodeName OBJECT-TYPE
  SYNTAX      IscsiName
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "This node's iSCSI name, which is independent of the location
     of the node, and can be resolved into a set of addresses
     through various discovery services."
 ::= { iscsiNodeAttributesEntry 2 }

iscsiNodeAlias OBJECT-TYPE
  SYNTAX      SnmpAdminString
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "A character string that is a human-readable name or
     description of the iSCSI node. If configured, this alias
     may be communicated to the initiator or target node at
     the remote end of the connection during a Login Request
     or Response message. This string is not used as an
     identifier, but it can be displayed by the system's user
     interface in a list of initiators and/or targets to
     which it is connected.

    If no alias exists, the value is a zero-length string."
  REFERENCE
    "RFC 7143, Sections 13.6 (TargetAlias) and 13.7
     (InitiatorAlias)"
 ::= { iscsiNodeAttributesEntry 3 }

iscsiNodeRoles OBJECT-TYPE

```

```

SYNTAX      BITS {
            targetTypeNode(0),
            initiatorTypeNode(1)
        }
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
    "A node can operate in one or both of two roles:
     a target role and/or an initiator role. If the node
     will operate in both roles, both bits must be set.

This object will also define the corresponding rows that
will exist in the iscsiTargetAttributesTable, the
iscsiInitiatorAttributesTable, or both. If the
targetTypeNode bit is set, there will be a corresponding
iscsiTargetAttributesEntry. If the initiatorTypeNode bit
is set, there will be a corresponding
iscsiInitiatorAttributesEntry. If both bits are set,
there will be a corresponding iscsiTgtPortalAttributesEntry
and iscsiPortalAttributesEntry."
 ::= { iscsiNodeAttributesEntry 4 }

iscsiNodeTransportType OBJECT-TYPE
SYNTAX      RowPointer
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
    "A pointer to the corresponding row in the appropriate
     table for this SCSI transport, thereby allowing management
     stations to locate the SCSI-level device that is represented
     by this iscsiNode. For example, it will usually point to the
     corresponding scsiTrnspt object in the SCSI MIB module.
     If no corresponding row exists, the value 0.0 must be
     used to indicate this."
REFERENCE
    "SCSI-MIB, RFC 4455, Section 9, Object Definitions,
     scsiTransportTypes"
 ::= { iscsiNodeAttributesEntry 5 }

iscsiNodeInitialR2T OBJECT-TYPE
SYNTAX      TruthValue
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
    "This object indicates the InitialR2T preference for this
     node:
     true = YES,
     false = will try to negotiate NO, will accept YES "

```

```

REFERENCE
  "RFC 7143, Section 13.10, InitialR2T"
 ::= { iscsiNodeAttributesEntry 6 }

iscsiNodeImmediateData OBJECT-TYPE
  SYNTAX      TruthValue
  MAX-ACCESS  read-write
  STATUS      current
  DESCRIPTION
    "This object indicates ImmediateData preference for this
     node:
      true = YES (but will accept NO),
      false = NO "
  REFERENCE
    "RFC 7143, Section 13.11, ImmediateData"
    DEFVAL      { true }
 ::= { iscsiNodeAttributesEntry 7 }

iscsiNodeMaxOutstandingR2T OBJECT-TYPE
  SYNTAX      Unsigned32 (1..65535)
  UNITS      "R2Ts"
  MAX-ACCESS  read-write
  STATUS      current
  DESCRIPTION
    "Maximum number of outstanding requests-to-transmit (R2Ts)
     allowed per iSCSI task."
  REFERENCE
    "RFC 7143, Section 13.17, MaxOutstandingR2T"
    DEFVAL      { 1 }
 ::= { iscsiNodeAttributesEntry 8 }

iscsiNodeFirstBurstLength OBJECT-TYPE
  SYNTAX      Unsigned32 (512..16777215)
  UNITS      "bytes"
  MAX-ACCESS  read-write
  STATUS      current
  DESCRIPTION
    "The maximum length (bytes) supported for unsolicited data
     to/from this node."
  REFERENCE
    "RFC 7143, Section 13.14, FirstBurstLength"
    DEFVAL      { 65536 }
 ::= { iscsiNodeAttributesEntry 9 }

iscsiNodeMaxBurstLength OBJECT-TYPE
  SYNTAX      Unsigned32 (512..16777215)
  UNITS      "bytes"
  MAX-ACCESS  read-write

```

```

STATUS          current
DESCRIPTION
"The maximum number of bytes that can be sent within
a single sequence of Data-In or Data-Out PDUs."
REFERENCE
"RFC 7143, Section 13.13, MaxBurstLength"
DEFVAL         { 262144 }
 ::= { iscsiNodeAttributesEntry 10 }

iscsiNodeMaxConnections OBJECT-TYPE
SYNTAX          Unsigned32 (1..65535)
UNITS           "connections"
MAX-ACCESS      read-write
STATUS          current
DESCRIPTION
"The maximum number of connections allowed in each
session to and/or from this node."
REFERENCE
"RFC 7143, Section 13.2, MaxConnections"
DEFVAL         { 1 }
 ::= { iscsiNodeAttributesEntry 11 }

iscsiNodeDataSequenceInOrder OBJECT-TYPE
SYNTAX          TruthValue
MAX-ACCESS      read-write
STATUS          current
DESCRIPTION
"The DataSequenceInOrder preference of this node.
False (=No) indicates that iSCSI data PDU sequences may
be transferred in any order. True (=Yes) indicates that
data PDU sequences must be transferred using
continuously increasing offsets, except during
error recovery."
REFERENCE
"RFC 7143, Section 13.19, DataSequenceInOrder"
DEFVAL         { true }
 ::= { iscsiNodeAttributesEntry 12 }

iscsiNodeDataPDUInOrder OBJECT-TYPE
SYNTAX          TruthValue
MAX-ACCESS      read-write
STATUS          current
DESCRIPTION
"The DataPDUInOrder preference of this node.
False (=No) indicates that iSCSI data PDUs within sequences
may be in any order. True (=Yes) indicates that data PDUs
within sequences must be at continuously increasing
addresses, with no gaps or overlay between PDUs."

```

```

REFERENCE
    "RFC 7143, Section 13.18, DataPDUInOrder"
DEFVAL      { true }
 ::= { iscsiNodeAttributesEntry 13 }

iscsiNodeDefaultTime2Wait OBJECT-TYPE
    SYNTAX      Unsigned32 (0..3600)
    UNITS      "seconds"
    MAX-ACCESS  read-write
    STATUS     current
    DESCRIPTION
        "The DefaultTime2Wait preference of this node. This is the
         minimum time, in seconds, to wait before attempting an
         explicit/implicit logout or active iSCSI task reassignment
         after an unexpected connection termination or a connection
         reset."
REFERENCE
    "RFC 7143, Section 13.15, DefaultTime2Wait"
DEFVAL      { 2 }
 ::= { iscsiNodeAttributesEntry 14 }

iscsiNodeDefaultTime2Retain OBJECT-TYPE
    SYNTAX      Unsigned32 (0..3600)
    UNITS      "seconds"
    MAX-ACCESS  read-write
    STATUS     current
    DESCRIPTION
        "The DefaultTime2Retain preference of this node. This is
         the maximum time, in seconds after an initial wait
         (Time2Wait), before which an active iSCSI task reassignment
         is still possible after an unexpected connection termination
         or a connection reset."
REFERENCE
    "RFC 7143, Section 13.16, DefaultTime2Retain"
DEFVAL      { 20 }
 ::= { iscsiNodeAttributesEntry 15 }

iscsiNodeErrorRecoveryLevel OBJECT-TYPE
    SYNTAX      Unsigned32 (0..255)
    MAX-ACCESS  read-write
    STATUS     current
    DESCRIPTION
        "The ErrorRecoveryLevel preference of this node.
         Currently, only 0-2 are valid.

This object is designed to accommodate future error-recovery
levels.

```

Higher error-recovery levels imply support in addition to support for the lower error level functions. In other words, error level 2 implies support for levels 0-1, since those functions are subsets of error level 2."

## REFERENCE

```
"RFC 7143, Section 13.20, ErrorRecoveryLevel"
DEFVAL { 0 }
 ::= { iscsiNodeAttributesEntry 16 }
```

## iscsiNodeDiscontinuityTime OBJECT-TYPE

SYNTAX	TimeStamp
MAX-ACCESS	read-only
STATUS	current

## DESCRIPTION

"The value of SysUpTime on the most recent occasion at which any one or more of this node's counters suffered a discontinuity.

If no such discontinuities have occurred since the last re-initialization of the local management subsystem, then this object contains a zero value."

```
 ::= { iscsiNodeAttributesEntry 17 }
```

## iscsiNodeStorageType OBJECT-TYPE

SYNTAX	StorageType
MAX-ACCESS	read-write
STATUS	current

## DESCRIPTION

"The storage type for all read-write objects within this row. Rows in this table are always created via an external process (e.g., not created via this MIB module). Conceptual rows having the value 'permanent' need not allow Write access to any columnar objects in the row.

If this object has the value 'volatile', modifications to read-write objects in this row are not persistent across reboots. If this object has the value 'nonVolatile', modifications to objects in this row are persistent.

An implementation may choose to allow this object to be set to either 'nonVolatile' or 'volatile', allowing the management application to choose this behavior."

```
DEFVAL { volatile }
 ::= { iscsiNodeAttributesEntry 18 }
```

---

```

iscsiTarget OBJECT IDENTIFIER ::= { iscsiObjects 6 }

-- Target Attributes Table

iscsiTargetAttributesTable OBJECT-TYPE
  SYNTAX      SEQUENCE OF IscsiTargetAttributesEntry
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "A list of iSCSI nodes that can take on a target role,
     belonging to each iSCSI instance present on the local
     system."
 ::= { iscsiTarget 1 }

iscsiTargetAttributesEntry OBJECT-TYPE
  SYNTAX      IscsiTargetAttributesEntry
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "An entry (row) containing management information applicable
     to a particular node that can take on a target role."
  INDEX { iscsiInstIndex, iscsiNodeIndex }
 ::= { iscsiTargetAttributesTable 1 }

IscsiTargetAttributesEntry ::= SEQUENCE {
  iscsiTgtLoginFailures          Counter32,
  iscsiTgtLastFailureTime        TimeStamp,
  iscsiTgtLastFailureType        AutonomousType,
  iscsiTgtLastIntrFailureName    IscsiName,
  iscsiTgtLastIntrFailureAddrType InetAddressType,
  iscsiTgtLastIntrFailureAddr    InetAddress,
  iscsiTgtLastIntrFailurePort    InetPortNumber
}

iscsiTgtLoginFailures OBJECT-TYPE
  SYNTAX      Counter32
  UNITS      "failed login attempts"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "This object counts the number of times a login attempt to this
     local target has failed.
     If this counter has suffered a discontinuity, the time of the
     last discontinuity is indicated in iscsiNodeDiscontinuityTime."
  REFERENCE
    "RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
 ::= { iscsiTargetAttributesEntry 1 }

```

```

iscsiTgtLastFailureTime OBJECT-TYPE
    SYNTAX          TimeStamp
    MAX-ACCESS     read-only
    STATUS         current
    DESCRIPTION
        "The timestamp of the most recent failure of a login attempt
        to this target. A value of zero indicates that no such
        failures have occurred since the last system boot."
::= { iscsiTargetAttributesEntry 2 }

iscsiTgtLastFailureType OBJECT-TYPE
    SYNTAX          AutonomousType
    MAX-ACCESS     read-only
    STATUS         current
    DESCRIPTION
        "The type of the most recent failure of a login attempt
        to this target, represented as the OID of the counter
        object in iscsiTargetLoginStatsTable for which the
        relevant instance was incremented. If no such failures
        have occurred since the last system boot, this attribute
        will have the value 0.0. A value of 0.0 may also be used
        to indicate a type that is not represented by any of
        the counters in iscsiTargetLoginStatsTable."
::= { iscsiTargetAttributesEntry 3 }

iscsiTgtLastIntrFailureName OBJECT-TYPE
    SYNTAX          IscsiName
    MAX-ACCESS     read-only
    STATUS         current
    DESCRIPTION
        "The iSCSI name of the initiator that failed the last
        login attempt. If no such failures have occurred since
        the last system boot, this value is a zero-length string."
::= { iscsiTargetAttributesEntry 4 }

iscsiTgtLastIntrFailureAddrType OBJECT-TYPE
    SYNTAX          InetAddressType
    MAX-ACCESS     read-only
    STATUS         current
    DESCRIPTION
        "The type of Internet Network Address contained in the
        corresponding instance of the iscsiTgtLastIntrFailureAddr.
        The value 'dns' is not allowed. If no such failures have
        occurred since the last system boot, this value is zero."
::= { iscsiTargetAttributesEntry 5 }

iscsiTgtLastIntrFailureAddr OBJECT-TYPE
    SYNTAX          InetAddress

```

```

MAX-ACCESS      read-only
STATUS         current
DESCRIPTION
    "An Internet Network Address, of the type specified by
    the object iscsiTgtLastIntrFailureAddrType, giving the
    host address of the initiator that failed the last login
    attempt. If no such failures have occurred since the last
    system boot, this value is a zero-length string."
 ::= { iscsiTargetAttributesEntry 6 }

iscsiTgtLastIntrFailurePort OBJECT-TYPE
    SYNTAX          InetPortNumber
    MAX-ACCESS     read-only
    STATUS         current
    DESCRIPTION
        "The transport protocol port number used by the initiator
        that failed the last login attempt. If no such failures
        have occurred since the last system boot, this value is a
        zero-length string."
 ::= { iscsiTargetAttributesEntry 7 }

-- Target Login Stats Table

iscsiTargetLoginStatsTable OBJECT-TYPE
    SYNTAX          SEQUENCE OF IscsiTargetLoginStatsEntry
    MAX-ACCESS     not-accessible
    STATUS         current
    DESCRIPTION
        "A table of counters that keep a record of the results
        of initiators' login attempts to this target."
 ::= { iscsiTarget 2 }

iscsiTargetLoginStatsEntry OBJECT-TYPE
    SYNTAX          IscsiTargetLoginStatsEntry
    MAX-ACCESS     not-accessible
    STATUS         current
    DESCRIPTION
        "An entry (row) containing counters for each result of
        a login attempt to this target."
    AUGMENTS { iscsiTargetAttributesEntry }
 ::= { iscsiTargetLoginStatsTable 1 }

IscsiTargetLoginStatsEntry ::= SEQUENCE {
    iscsiTgtLoginAccepts          Counter32,
    iscsiTgtLoginOtherFails       Counter32,
    iscsiTgtLoginRedirects        Counter32,
    iscsiTgtLoginAuthorizeFails   Counter32,
    iscsiTgtAuthenticateFails     Counter32,
}

```

```

    iscsiTgtLoginNegotiateFails    Counter32
}

iscsiTgtLoginAccepts OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "successful logins"
    MAX-ACCESS  read-only
    STATUS     current
    DESCRIPTION
        "The count of Login Response PDUs with status
         0x0000, Accept Login, transmitted by this
         target.
         If this counter has suffered a discontinuity, the time of the
         last discontinuity is indicated in iscsiNodeDiscontinuityTime."
    REFERENCE
        "RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
::= { iscsiTargetLoginStatsEntry 1 }

iscsiTgtLoginOtherFails OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "failed logins"
    MAX-ACCESS  read-only
    STATUS     current
    DESCRIPTION
        "The number of Login Response PDUs that were transmitted
         by this target and that were not counted by any other
         object in the row.
         If this counter has suffered a discontinuity, the time of the
         last discontinuity is indicated in iscsiNodeDiscontinuityTime."
    REFERENCE
        "RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
::= { iscsiTargetLoginStatsEntry 2 }

iscsiTgtLoginRedirects OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "redirected logins"
    MAX-ACCESS  read-only
    STATUS     current
    DESCRIPTION
        "The count of Login Response PDUs with status class 0x01,
         Redirection, transmitted by this target.
         If this counter has suffered a discontinuity, the time of the
         last discontinuity is indicated in iscsiNodeDiscontinuityTime."
    REFERENCE
        "RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
::= { iscsiTargetLoginStatsEntry 3 }

iscsiTgtLoginAuthorizeFails OBJECT-TYPE

```

```

SYNTAX      Counter32
UNITS      "failed logins"
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
"The count of Login Response PDUs with status 0x0202,
Forbidden Target, transmitted by this target.

If this counter is incremented, an iscsiTgtLoginFailure
notification should be generated.
If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiNodeDiscontinuityTime."
REFERENCE
"RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
::= { iscsiTargetLoginStatsEntry 4 }

iscsiTgtLoginAuthenticateFails OBJECT-TYPE
SYNTAX      Counter32
UNITS      "failed logins"
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
"The count of Login Response PDUs with status 0x0201,
Authentication Failed, transmitted by this target.

If this counter is incremented, an iscsiTgtLoginFailure
notification should be generated.

If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiNodeDiscontinuityTime."
REFERENCE
"RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
::= { iscsiTargetLoginStatsEntry 5 }

iscsiTgtLoginNegotiateFails OBJECT-TYPE
SYNTAX      Counter32
UNITS      "failed logins"
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
"The number of times a target has effectively refused a
login because the parameter negotiation failed.
If this counter is incremented, an iscsiTgtLoginFailure
notification should be generated.
If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiNodeDiscontinuityTime."
::= { iscsiTargetLoginStatsEntry 6 }

```

```
-- Target Logout Stats Table

iscsiTargetLogoutStatsTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF IscsiTargetLogoutStatsEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "When a target receives a Logout command, it responds
         with a Logout Response that carries a status code.
         This table contains counters for both normal and
         abnormal Logout Requests received by this target."
 ::= { iscsiTarget 3 }

iscsiTargetLogoutStatsEntry OBJECT-TYPE
    SYNTAX      IscsiTargetLogoutStatsEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "An entry (row) containing counters of Logout Response
         PDUs that were received by this target."
    AUGMENTS { iscsiTargetAttributesEntry }
 ::= { iscsiTargetLogoutStatsTable 1 }

IscsiTargetLogoutStatsEntry ::= SEQUENCE {
    iscsiTgtLogoutNormals          Counter32,
    iscsiTgtLogoutOthers           Counter32,
    iscsiTgtLogoutCxnClosed        Counter32,
    iscsiTgtLogoutCxnRemoved       Counter32
}

iscsiTgtLogoutNormals OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "normal logouts"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The count of Logout Command PDUs received by this target,
         with reason code 0 (closes the session).
         If this counter has suffered a discontinuity, the time of the
         last discontinuity is indicated in iscsiNodeDiscontinuityTime."
    REFERENCE
        "RFC 7143, Section 11.14.1, Reason Code"
 ::= { iscsiTargetLogoutStatsEntry 1 }

iscsiTgtLogoutOthers OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "abnormal logouts"
    MAX-ACCESS  read-only
```

```

STATUS          current
DESCRIPTION
  "The count of Logout Command PDUs received by this target,
  with any reason code other than 0.
  If this counter has suffered a discontinuity, the time of the
  last discontinuity is indicated in iscsiNodeDiscontinuityTime."
REFERENCE
  "RFC 7143, Section 11.14.1, Reason Code"
::= { iscsiTargetLogoutStatsEntry 2 }

iscsiTgtLogoutCxnClosed OBJECT-TYPE
  SYNTAX        Counter32
  UNITS         "abnormal logouts"
  MAX-ACCESS    read-only
  STATUS        current
  DESCRIPTION
    "The count of Logout Command PDUs received by this target,
    with reason code 1 (closes the connection).
    If this counter has suffered a discontinuity, the time of the
    last discontinuity is indicated in iscsiNodeDiscontinuityTime."
  REFERENCE
    "RFC 7143, Section 11.14.1, Reason Code"
::= { iscsiTargetLogoutStatsEntry 3 }

iscsiTgtLogoutCxnRemoved OBJECT-TYPE
  SYNTAX        Counter32
  UNITS         "abnormal logouts"
  MAX-ACCESS    read-only
  STATUS        current
  DESCRIPTION
    "The count of Logout Command PDUs received by this target,
    with reason code 2 (removes the connection).
    If this counter has suffered a discontinuity, the time of the
    last discontinuity is indicated in iscsiNodeDiscontinuityTime."
  REFERENCE
    "RFC 7143, Section 11.14.1, Reason Code"
::= { iscsiTargetLogoutStatsEntry 4 }

*****  

iscsiTgtAuthorization OBJECT IDENTIFIER ::= { iscsiObjects 7 }

-- Target Authorization Attributes Table

iscsiTgtAuthAttributesTable OBJECT-TYPE
  SYNTAX        SEQUENCE OF IscsiTgtAuthAttributesEntry
  MAX-ACCESS    not-accessible
  STATUS        current

```

```

DESCRIPTION
    "A list of initiator identities that are authorized to
     access each target node within each iSCSI instance
     present on the local system."
 ::= { iscsiTgtAuthorization 1 }

iscsiTgtAuthAttributesEntry OBJECT-TYPE
    SYNTAX      IscsiTgtAuthAttributesEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "An entry (row) containing management information
         applicable to a particular target node's authorized
         initiator identity."
    INDEX { iscsiInstIndex, iscsiNodeIndex, iscsiTgtAuthIndex }
 ::= { iscsiTgtAuthAttributesTable 1 }

IscsiTgtAuthAttributesEntry ::= SEQUENCE {
    iscsiTgtAuthIndex          Unsigned32,
    iscsiTgtAuthRowStatus       RowStatus,
    iscsiTgtAuthIdentity        RowPointer,
    iscsiTgtAuthStorageType     StorageType
}

iscsiTgtAuthIndex OBJECT-TYPE
    SYNTAX      Unsigned32 (1..4294967295)
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "An arbitrary integer used to uniquely identify a particular
         target's authorized initiator identity within an iSCSI
         instance present on the local system. This index value must
         not be modified or reused by an agent unless a reboot has
         occurred. An agent should attempt to keep this value
         persistent across reboots."
 ::= { iscsiTgtAuthAttributesEntry 1 }

iscsiTgtAuthRowStatus OBJECT-TYPE
    SYNTAX      RowStatus
    MAX-ACCESS  read-create
    STATUS      current
    DESCRIPTION
        "This field allows entries to be dynamically added and
         removed from this table via SNMP. When adding a row to
         this table, all non-Index/RowStatus objects must be set.
         When the value of this object is 'active', the values of
         the other objects in this table cannot be changed.
         Rows may be discarded using RowStatus."

```

```

 ::= { iscsiTgtAuthAttributesEntry 2 }

iscsiTgtAuthIdentity OBJECT-TYPE
    SYNTAX      RowPointer
    MAX-ACCESS  read-create
    STATUS      current
    DESCRIPTION
        "A pointer to the corresponding user entry in the IPS-AUTH
         MIB module that will be allowed to access this iSCSI target."
    REFERENCE
        "IPS-AUTH MIB, RFC 4545, Section 7.3, ipsAuthIdentity"
 ::= { iscsiTgtAuthAttributesEntry 3 }

iscsiTgtAuthStorageType OBJECT-TYPE
    SYNTAX      StorageType
    MAX-ACCESS  read-create
    STATUS      current
    DESCRIPTION
        "The storage type for this row. Rows in this table that were
         created through an external process (e.g., not created via
         this MIB) may have a storage type of readOnly or permanent.

         Conceptual rows having the value 'permanent' need not
         allow write access to any columnar objects in the row."
    DEFVAL      { nonVolatile }
 ::= { iscsiTgtAuthAttributesEntry 4 }

--*****


iscsiInitiator OBJECT IDENTIFIER ::= { iscsiObjects 8 }

-- Initiator Attributes Table

iscsiInitiatorAttributesTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF IscsiInitiatorAttributesEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "A list of iSCSI nodes that can take on an initiator
         role, belonging to each iSCSI instance present on
         the local system."
 ::= { iscsiInitiator 1 }

iscsiInitiatorAttributesEntry OBJECT-TYPE
    SYNTAX      IscsiInitiatorAttributesEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION

```

```

    "An entry (row) containing management information
    applicable to a particular iSCSI node that has
    initiator capabilities."
INDEX { iscsiInstIndex, iscsiNodeIndex }
::= { iscsiInitiatorAttributesTable 1 }

IscsiInitiatorAttributesEntry ::= SEQUENCE {
    iscsiIntrLoginFailures          Counter32,
    iscsiIntrLastFailureTime        TimeStamp,
    iscsiIntrLastFailureType        AutonomousType,
    iscsiIntrLastTgtFailureName    IscsiName,
    iscsiIntrLastTgtFailureAddrType InetAddressType,
    iscsiIntrLastTgtFailureAddr     InetAddress,
    iscsiIntrLastTgtFailurePort     InetPortNumber
}

iscsiIntrLoginFailures OBJECT-TYPE
SYNTAX      Counter32
UNITS       "failed logins"
MAX-ACCESS   read-only
STATUS      current
DESCRIPTION
    "This object counts the number of times a login attempt from
    this local initiator has failed.
    If this counter has suffered a discontinuity, the time of the
    last discontinuity is indicated in iscsiNodeDiscontinuityTime."
REFERENCE
    "RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
::= { iscsiInitiatorAttributesEntry 1 }

iscsiIntrLastFailureTime OBJECT-TYPE
SYNTAX      TimeStamp
MAX-ACCESS   read-only
STATUS      current
DESCRIPTION
    "The timestamp of the most recent failure of a login attempt
    from this initiator. A value of zero indicates that no such
    failures have occurred since the last system boot."
::= { iscsiInitiatorAttributesEntry 2 }

iscsiIntrLastFailureType OBJECT-TYPE
SYNTAX      AutonomousType
MAX-ACCESS   read-only
STATUS      current
DESCRIPTION
    "The type of the most recent failure of a login attempt
    from this initiator, represented as the OID of the counter
    object in iscsiInitiatorLoginStatsTable for which the

```

relevant instance was incremented. If no such failures have occurred since the last system boot, this attribute will have the value 0.0. A value of 0.0 may also be used to indicate a type that is not represented by any of the counters in iscsiInitiatorLoginStatsTable."

```
 ::= { iscsiInitiatorAttributesEntry 3 }

iscsiIntrLastTgtFailureName OBJECT-TYPE
    SYNTAX      IscsiName
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "A UTF-8 string giving the name of the target that failed
         the last login attempt. If no such failures have occurred
         since the last system boot, this value is a zero-length string."
 ::= { iscsiInitiatorAttributesEntry 4 }

iscsiIntrLastTgtFailureAddrType OBJECT-TYPE
    SYNTAX      InetAddressType
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The type of Internet Network Address contained in the
         corresponding instance of the iscsiIntrLastTgtFailureAddr.
         The value 'dns' is not allowed. If no such failures have
         occurred since the last system boot, this value is zero."
 ::= { iscsiInitiatorAttributesEntry 5 }

iscsiIntrLastTgtFailureAddr OBJECT-TYPE
    SYNTAX      InetAddress
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "An Internet Network Address, of the type specified by the
         object iscsiIntrLastTgtFailureAddrType, giving the host
         address of the target that failed the last login attempt.
         If no such failures have occurred since the last system boot,
         this value is a zero-length string."
 ::= { iscsiInitiatorAttributesEntry 6 }

iscsiIntrLastTgtFailurePort OBJECT-TYPE
    SYNTAX      InetPortNumber
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The transport protocol port number used by the target
         that failed the last login attempt.
         If no such failures have occurred since the last system boot,
```

```

        this value is a zero-length string."
 ::= { iscsiInitiatorAttributesEntry 7 }

-- Initiator Login Stats Table

iscsiInitiatorLoginStatsTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF IscsiInitiatorLoginStatsEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "A table of counters that keep track of the results of
         this initiator's login attempts."
 ::= { iscsiInitiator 2 }

iscsiInitiatorLoginStatsEntry OBJECT-TYPE
    SYNTAX      IscsiInitiatorLoginStatsEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "An entry (row) containing counters of each result
         of this initiator's login attempts."
    AUGMENTS { iscsiInitiatorAttributesEntry }
 ::= { iscsiInitiatorLoginStatsTable 1 }

IscsiInitiatorLoginStatsEntry ::= SEQUENCE {
    iscsiIntrLoginAcceptRsp          Counter32,
    iscsiIntrLoginOtherFailRsp       Counter32,
    iscsiIntrLoginRedirectRsp        Counter32,
    iscsiIntrLoginAuthFailRsp        Counter32,
    iscsiIntrLoginAuthenticateFails Counter32,
    iscsiIntrLoginNegotiateFails    Counter32,
    iscsiIntrLoginAuthorizeFails    Counter32
}

iscsiIntrLoginAcceptRsp OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "successful logins"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The count of Login Response PDUs with status
         0x0000, Accept Login, received by this initiator.
         If this counter has suffered a discontinuity, the time of the
         last discontinuity is indicated in iscsiNodeDiscontinuityTime."
    REFERENCE
        "RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
 ::= { iscsiInitiatorLoginStatsEntry 1 }

```

```

iscsiIntrLoginOtherFailRsp OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "failed logins"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The count of Login Response PDUs received by this
         initiator with any status code not counted in the
         objects below.
         If this counter has suffered a discontinuity, the time of the
         last discontinuity is indicated in iscsiNodeDiscontinuityTime."
    REFERENCE
        "RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
    ::= { iscsiInitiatorLoginStatsEntry 2 }

iscsiIntrLoginRedirectRsp OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "failed logins"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The count of Login Response PDUs with status class 0x01,
         Redirection, received by this initiator.
         If this counter has suffered a discontinuity, the time of the
         last discontinuity is indicated in iscsiNodeDiscontinuityTime."
    REFERENCE
        "RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
    ::= { iscsiInitiatorLoginStatsEntry 3 }

iscsiIntrLoginAuthFailRsp OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "failed logins"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The count of Login Response PDUs with status class 0x201,
         Authentication Failed, received by this initiator.
         If this counter has suffered a discontinuity, the time of the
         last discontinuity is indicated in iscsiNodeDiscontinuityTime."
    REFERENCE
        "RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
    ::= { iscsiInitiatorLoginStatsEntry 4 }

iscsiIntrLoginAuthenticateFails OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "failed logins"
    MAX-ACCESS  read-only
    STATUS      current

```

**DESCRIPTION**

"The number of times the initiator has aborted a login because the target could not be authenticated.

No response is generated.

If this counter is incremented, an iscsiIntrLoginFailure notification should be generated.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

**REFERENCE**

"RFC 7143, Section 11.13.5, Status-Class and Status-Detail"

`::= { iscsiInitiatorLoginStatsEntry 5 }`

**iscsiIntrLoginNegotiateFails OBJECT-TYPE**

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

**DESCRIPTION**

"The number of times the initiator has aborted a login because parameter negotiation with the target failed.

No response is generated.

If this counter is incremented, an iscsiIntrLoginFailure notification should be generated.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

**REFERENCE**

"RFC 7143, Section 7.12, Negotiation Failures"

`::= { iscsiInitiatorLoginStatsEntry 6 }`

**iscsiIntrLoginAuthorizeFails OBJECT-TYPE**

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

**DESCRIPTION**

"The count of Login Response PDUs with status 0x0202, Forbidden Target, received by this initiator.

If this counter is incremented, an iscsiIntrLoginFailure notification should be generated.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

**REFERENCE**

```

"RFC 7143, Section 11.13.5, Status-Class and Status-Detail"
 ::= { iscsiInitiatorLoginStatsEntry 7 }

-- Initiator Logout Stats Table

iscsiInitiatorLogoutStatsTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF IscsiInitiatorLogoutStatsEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "When an initiator attempts to send a Logout command, the target
         responds with a Logout Response that carries a status code.
         This table contains a list of counters of Logout Response
         PDUs of each status code that was received by each
         initiator belonging to this iSCSI instance present on this
         system."
 ::= { iscsiInitiator 3 }

iscsiInitiatorLogoutStatsEntry OBJECT-TYPE
    SYNTAX      IscsiInitiatorLogoutStatsEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "An entry (row) containing counters of Logout Response
         PDUs of each status code that was generated by this
         initiator."
    AUGMENTS { iscsiInitiatorAttributesEntry }
 ::= { iscsiInitiatorLogoutStatsTable 1 }

IscsiInitiatorLogoutStatsEntry ::= SEQUENCE {
    iscsiIntrLogoutNormals          Counter32,
    iscsiIntrLogoutOthers           Counter32
}

iscsiIntrLogoutNormals OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "normal logouts"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The count of Logout Command PDUs generated by this initiator
         with reason code 0 (closes the session).
         If this counter has suffered a discontinuity, the time of the
         last discontinuity is indicated in iscsiNodeDiscontinuityTime."
    REFERENCE
        "RFC 7143, Section 11.14.1, Reason Code"
 ::= { iscsiInitiatorLogoutStatsEntry 1 }

```

```

iscsiIntrLogoutOthers OBJECT-TYPE
  SYNTAX          Counter32
  UNITS          "abnormal logouts"
  MAX-ACCESS    read-only
  STATUS         current
  DESCRIPTION
    "The count of Logout Command PDUs generated by this initiator
     with any status code other than 0.
     If this counter has suffered a discontinuity, the time of the
     last discontinuity is indicated in iscsiNodeDiscontinuityTime."
  REFERENCE
    "RFC 7143, Section 11.14.1, Reason Code"

 ::= { iscsiInitiatorLogoutStatsEntry 2 }

--*****



iscsiIntrAuthorization OBJECT IDENTIFIER ::= { iscsiObjects 9 }

-- Initiator Authorization Attributes Table

iscsiIntrAuthAttributesTable OBJECT-TYPE
  SYNTAX          SEQUENCE OF IscsiIntrAuthAttributesEntry
  MAX-ACCESS    not-accessible
  STATUS         current
  DESCRIPTION
    "A list of target identities that each initiator
     on the local system may access."
 ::= { iscsiIntrAuthorization 1 }

iscsiIntrAuthAttributesEntry OBJECT-TYPE
  SYNTAX          IscsiIntrAuthAttributesEntry
  MAX-ACCESS    not-accessible
  STATUS         current
  DESCRIPTION
    "An entry (row) containing management information applicable
     to a particular initiator node's authorized target identity."
  INDEX { iscsiInstIndex, iscsiNodeIndex, iscsiIntrAuthIndex }
 ::= { iscsiIntrAuthAttributesTable 1 }

IscsiIntrAuthAttributesEntry ::= SEQUENCE {
  iscsiIntrAuthIndex          Unsigned32,
  iscsiIntrAuthRowStatus       RowStatus,
  iscsiIntrAuthIdentity        RowPointer,
  iscsiIntrAuthStorageType     StorageType
}

iscsiIntrAuthIndex OBJECT-TYPE

```

```

SYNTAX      Unsigned32 (1..4294967295)
MAX-ACCESS  not-accessible
STATUS      current
DESCRIPTION
  "An arbitrary integer used to uniquely identify a
  particular initiator node's authorized target
  identity within an iSCSI instance present on the
  local system. This index value must not be modified
  or reused by an agent unless a reboot has occurred.
  An agent should attempt to keep this value persistent
  across reboots."
 ::= { iscsiIntrAuthAttributesEntry 1 }

iscsiIntrAuthRowStatus OBJECT-TYPE
  SYNTAX      RowStatus
  MAX-ACCESS  read-create
  STATUS      current
  DESCRIPTION
    "This field allows entries to be dynamically added and
    removed from this table via SNMP. When adding a row to
    this table, all non-Index/RowStatus objects must be set.
    When the value of this object is 'active', the values of
    the other objects in this table cannot be changed.
    Rows may be discarded using RowStatus."
 ::= { iscsiIntrAuthAttributesEntry 2 }

iscsiIntrAuthIdentity OBJECT-TYPE
  SYNTAX      RowPointer
  MAX-ACCESS  read-create
  STATUS      current
  DESCRIPTION
    "A pointer to the corresponding user entry in the IPS-AUTH
    MIB module to which this initiator node should attempt to
    establish an iSCSI session."
  REFERENCE
    "IPS-AUTH MIB, RFC 4545, Section 7.3, ipsAuthIdentity"
 ::= { iscsiIntrAuthAttributesEntry 3 }

iscsiIntrAuthStorageType OBJECT-TYPE
  SYNTAX      StorageType
  MAX-ACCESS  read-create
  STATUS      current
  DESCRIPTION
    "The storage type for this row. Rows in this table that were
    created through an external process (e.g., not created via
    this MIB) may have a storage type of readOnly or permanent.

    Conceptual rows having the value 'permanent' need not

```

```

    allow write access to any columnar objects in the row."
DEFVAL      { nonVolatile }
 ::= { iscsiIntrAuthAttributesEntry 4 }

--*****


iscsiSession OBJECT IDENTIFIER ::= { iscsiObjects 10 }

-- Session Attributes Table

iscsiSessionAttributesTable OBJECT-TYPE
SYNTAX      SEQUENCE OF IscsiSessionAttributesEntry
MAX-ACCESS  not-accessible
STATUS      current
DESCRIPTION
"A list of sessions belonging to each iSCSI instance
present on the system."
 ::= { iscsiSession 1 }

iscsiSessionAttributesEntry OBJECT-TYPE
SYNTAX      IscsiSessionAttributesEntry
MAX-ACCESS  not-accessible
STATUS      current
DESCRIPTION
"An entry (row) containing management information applicable
to a particular session.

If this session is a discovery session that is not attached
to any particular node, the iscsiSsnNodeIndex will be zero.
Otherwise, the iscsiSsnNodeIndex will have the same value as
iscsiNodeIndex."
INDEX { iscsiInstIndex, iscsiSsnNodeIndex, iscsiSsnIndex }
 ::= { iscsiSessionAttributesTable 1 }

IscsiSessionAttributesEntry ::= SEQUENCE {
  iscsiSsnNodeIndex          Unsigned32,
  iscsiSsnIndex               Unsigned32,
  iscsiSsnDirection          INTEGER,
  iscsiSsnInitiatorName      IscsiName,
  iscsiSsnTargetName          IscsiName,
  iscsiSsnTSIH                Unsigned32,
  iscsiSsnISID                OCTET STRING,
  iscsiSsnInitiatorAlias     SnmpAdminString,
  iscsiSsnTargetAlias         SnmpAdminString,
  iscsiSsnInitialR2T          TruthValue,
  iscsiSsnImmediateData      TruthValue,
  iscsiSsnType                 INTEGER,
  iscsiSsnMaxOutstandingR2T  Unsigned32,
}

```

```

iscsiSsnFirstBurstLength      Unsigned32,
iscsiSsnMaxBurstLength       Unsigned32,
iscsiSsnConnectionNumber     Gauge32,
iscsiSsnAuthIdentity        RowPointer,
iscsiSsnDataSequenceInOrder  TruthValue,
iscsiSsnDataPDUInOrder      TruthValue,
iscsiSsnErrorRecoveryLevel   Unsigned32,
iscsiSsnDiscontinuityTime    TimeStamp,
iscsiSsnProtocolLevel       Unsigned32,
iscsiSsnTaskReporting        BITS
}

iscsiSsnNodeIndex OBJECT-TYPE
  SYNTAX      Unsigned32 (0..4294967295)
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "An arbitrary integer used to uniquely identify a
     particular node within an iSCSI instance present
     on the local system. For normal, non-discovery
     sessions, this value will map to the iscsiNodeIndex.
     For discovery sessions that do not have a node
     associated, the value 0 (zero) is used."
 ::= { iscsiSessionAttributesEntry 1 }

iscsiSsnIndex OBJECT-TYPE
  SYNTAX      Unsigned32 (1..4294967295)
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "An arbitrary integer used to uniquely identify a
     particular session within an iSCSI instance present
     on the local system. An agent should attempt to
     not reuse index values unless a reboot has occurred.
     iSCSI sessions are destroyed during a reboot; rows
     in this table are not persistent across reboots."
 ::= { iscsiSessionAttributesEntry 2 }

iscsiSsnDirection OBJECT-TYPE
  SYNTAX      INTEGER {
                inboundSession(1),
                outboundSession(2)
              }
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "Direction of iSCSI session:
     inboundSession - session is established from an external

```

```

initiator to a target within this iSCSI
instance.

outboundSession - session is established from an initiator
within this iSCSI instance to an external
target."
 ::= { iscsiSessionAttributesEntry 3 }

iscsiSsnInitiatorName OBJECT-TYPE
  SYNTAX      IscsiName
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "If iscsiSsnDirection is Inbound, this object is a
    UTF-8 string that will contain the name of the remote
    initiator. If this session is a discovery session that
    does not specify a particular initiator, this object
    will contain a zero-length string.

    If iscsiSsnDirection is Outbound, this object will
    contain a zero-length string."
 ::= { iscsiSessionAttributesEntry 4 }

iscsiSsnTargetName OBJECT-TYPE
  SYNTAX      IscsiName
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "If iscsiSsnDirection is Outbound, this object is a
    UTF-8 string that will contain the name of the remote
    target. If this session is a discovery session that
    does not specify a particular target, this object will
    contain a zero-length string.

    If iscsiSsnDirection is Inbound, this object will
    contain a zero-length string."
 ::= { iscsiSessionAttributesEntry 5 }

iscsiSsnTSIH OBJECT-TYPE
  SYNTAX      Unsigned32 (1..65535)
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The target-defined identification handle for this session."
  REFERENCE
    "RFC 7143, Section 11.12.6, TSIH"
 ::= { iscsiSessionAttributesEntry 6 }

iscsiSsnISID OBJECT-TYPE

```

```

SYNTAX          OCTET STRING (SIZE(6))
MAX-ACCESS     read-only
STATUS         current
DESCRIPTION
    "The initiator-defined portion of the iSCSI Session ID."
REFERENCE
    "RFC 7143, Section 11.12.5, ISID"
 ::= { iscsiSessionAttributesEntry 7 }

iscsiSsnInitiatorAlias OBJECT-TYPE
    SYNTAX          SnmpAdminString
    MAX-ACCESS     read-only
    STATUS         current
    DESCRIPTION
        "A UTF-8 string that gives the alias communicated by the
         initiator end of the session during the login phase.

         If no alias exists, the value is a zero-length string."
REFERENCE
    "RFC 7143, Section 13.7, InitiatorAlias"
 ::= { iscsiSessionAttributesEntry 8 }

iscsiSsnTargetAlias OBJECT-TYPE
    SYNTAX          SnmpAdminString
    MAX-ACCESS     read-only
    STATUS         current
    DESCRIPTION
        "A UTF-8 string that gives the alias communicated by the
         target end of the session during the login phase.

         If no alias exists, the value is a zero-length string."
REFERENCE
    "RFC 7143, Section 13.6, TargetAlias"
 ::= { iscsiSessionAttributesEntry 9 }

iscsiSsnInitialR2T OBJECT-TYPE
    SYNTAX          TruthValue
    MAX-ACCESS     read-only
    STATUS         current
    DESCRIPTION
        "If set to true, indicates that the initiator must wait
         for an R2T before sending to the target.  If set to false,
         the initiator may send data immediately, within limits set
         by iscsiSsnFirstBurstLength and the expected data transfer
         length of the request."
REFERENCE
    "RFC 7143, Section 13.10, InitialR2T"
 ::= { iscsiSessionAttributesEntry 10 }

```

```

iscsiSsnImmediateData OBJECT-TYPE
  SYNTAX          TruthValue
  MAX-ACCESS     read-only
  STATUS         current
  DESCRIPTION
    "Indicates whether the initiator and target have agreed to
     support immediate data on this session."
  REFERENCE
    "RFC 7143, Section 13.11, ImmediateData"
 ::= { iscsiSessionAttributesEntry 11 }

iscsiSsnType OBJECT-TYPE

  SYNTAX          INTEGER {
                    normalSession(1),
                    discoverySession(2)
                  }
  MAX-ACCESS     read-only
  STATUS         current
  DESCRIPTION
    "Type of iSCSI session:
     normalSession - session is a normal iSCSI session
     discoverySession - session is being used only for discovery."
  REFERENCE
    "RFC 7143, Section 13.21, SessionType"
 ::= { iscsiSessionAttributesEntry 12 }

iscsiSsnMaxOutstandingR2T OBJECT-TYPE
  SYNTAX          Unsigned32 (1..65535)
  UNITS           "R2Ts"
  MAX-ACCESS     read-only
  STATUS         current
  DESCRIPTION
    "The maximum number of outstanding requests-to-transmit
     (R2Ts) per iSCSI task within this session."
  REFERENCE
    "RFC 7143, Section 13.17, MaxOutstandingR2T"
 ::= { iscsiSessionAttributesEntry 13 }

iscsiSsnFirstBurstLength OBJECT-TYPE
  SYNTAX          Unsigned32 (512..16777215)
  UNITS           "bytes"
  MAX-ACCESS     read-only
  STATUS         current
  DESCRIPTION
    "The maximum length supported for unsolicited data sent
     within this session."
  REFERENCE

```

```

"RFC 7143, Section 13.14, FirstBurstLength"
 ::= { iscsiSessionAttributesEntry 14 }

iscsiSsnMaxBurstLength OBJECT-TYPE
  SYNTAX      Unsigned32 (512..16777215)
  UNITS       "bytes"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The maximum number of bytes that can be sent within
     a single sequence of Data-In or Data-Out PDUs."
  REFERENCE
    "RFC 7143, Section 13.13, MaxBurstLength"
 ::= { iscsiSessionAttributesEntry 15 }

iscsiSsnConnectionNumber OBJECT-TYPE
  SYNTAX      Gauge32 (1..65535)
  UNITS       "connections"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The number of transport protocol connections that currently
     belong to this session."
 ::= { iscsiSessionAttributesEntry 16 }

iscsiSsnAuthIdentity OBJECT-TYPE
  SYNTAX      RowPointer
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "This object contains a pointer to a row in the
     IPS-AUTH MIB module that identifies the authentication
     identity being used on this session, as communicated
     during the login phase."
  REFERENCE
    "IPS-AUTH MIB, RFC 4545, Section 7.3, ipsAuthIdentity"
 ::= { iscsiSessionAttributesEntry 17 }

iscsiSsnDataSequenceInOrder OBJECT-TYPE
  SYNTAX      TruthValue
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "False indicates that iSCSI data PDU sequences may
     be transferred in any order. True indicates that
     data PDU sequences must be transferred using
     continuously increasing offsets, except during
     error recovery."

```

```

REFERENCE
  "RFC 7143, Section 13.19, DataSequenceInOrder"
 ::= { iscsiSessionAttributesEntry 18 }

iscsiSsnDataPDUInOrder OBJECT-TYPE
  SYNTAX      TruthValue
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "False indicates that iSCSI data PDUs within sequences
     may be in any order. True indicates that data PDUs
     within sequences must be at continuously increasing
     addresses, with no gaps or overlay between PDUs.
     Default is true."
  REFERENCE
    "RFC 7143, Section 13.18, DataPDUInOrder"
 ::= { iscsiSessionAttributesEntry 19 }

iscsiSsnErrorRecoveryLevel OBJECT-TYPE
  SYNTAX      Unsigned32 (0..255)
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The level of error recovery negotiated between
     the initiator and the target. Higher numbers
     represent more detailed recovery schemes."
  REFERENCE
    "RFC 7143, Section 13.20, ErrorRecoveryLevel"
 ::= { iscsiSessionAttributesEntry 20 }

iscsiSsnDiscontinuityTime OBJECT-TYPE
  SYNTAX      TimeStamp
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The value of SysUpTime on the most recent occasion
     at which any one or more of this session's counters
     suffered a discontinuity.
     When a session is established, and this object is
     created, it is initialized to the current value
     of SysUpTime."
 ::= { iscsiSessionAttributesEntry 21 }

iscsiSsnProtocolLevel OBJECT-TYPE
  SYNTAX      Unsigned32 (0..31)
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION

```

```

    "The iSCSI protocol level negotiated for this session."
REFERENCE
    "RFC 7144, Section 7.1.1, iSCSIProtocolLevel"
DEFVAL      { 1 }
 ::= { iscsiSessionAttributesEntry 22 }

iscsiSsnTaskReporting OBJECT-TYPE
SYNTAX      BITS {
                taskReportingRfc3720(0),
                taskReportingResponseFence(1),
                taskReportingFastAbort(2)
            }
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
    "This key is used to negotiate the task completion reporting
semantics from the SCSI target.

    Default value is taskReportingRfc3720."
REFERENCE
    "RFC 7143, Section 13.23, TaskReporting"
 ::= { iscsiSessionAttributesEntry 23 }

-- Session Stats Table

iscsiSessionStatsTable OBJECT-TYPE
SYNTAX      SEQUENCE OF IscsiSessionStatsEntry
MAX-ACCESS  not-accessible
STATUS      current
DESCRIPTION
    "A list of general iSCSI traffic counters for each of the
sessions present on the system."
 ::= { iscsiSession 2 }

iscsiSessionStatsEntry OBJECT-TYPE
SYNTAX      IscsiSessionStatsEntry
MAX-ACCESS  not-accessible
STATUS      current
DESCRIPTION
    "An entry (row) containing general iSCSI traffic counters
for a particular session."
AUGMENTS { iscsiSessionAttributesEntry }

 ::= { iscsiSessionStatsTable 1 }

IscsiSessionStatsEntry ::= SEQUENCE {
    iscsiSsnCmdPDUs          Counter32,

```

```

iscsiSsnRspPDUs          Counter32,
iscsiSsnTxDataOctets     Counter64,
iscsiSsnRxDataOctets     Counter64,
iscsiSsnLCTxDataOctets   Counter32,
iscsiSsnLCRxDataOctets   Counter32,
iscsiSsnNopReceivedPDUs Counter32,
iscsiSsnNopSentPDUs      Counter32
}

iscsiSsnCmdPDUs OBJECT-TYPE
  SYNTAX      Counter32
  UNITS       "PDUs"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The count of Command PDUs transferred on this session.
     If this counter has suffered a discontinuity, the time of the
     last discontinuity is indicated in iscsiSsnDiscontinuityTime."
 ::= { iscsiSessionStatsEntry 1 }

iscsiSsnRspPDUs OBJECT-TYPE
  SYNTAX      Counter32
  UNITS       "PDUs"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The count of Response PDUs transferred on this session.
     If this counter has suffered a discontinuity, the time of the
     last discontinuity is indicated in iscsiSsnDiscontinuityTime."
 ::= { iscsiSessionStatsEntry 2 }

iscsiSsnTxDataOctets OBJECT-TYPE
  SYNTAX      Counter64
  UNITS       "octets"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The count of data octets that were transmitted by
     the local iSCSI node on this session.
     If this counter has suffered a discontinuity, the time of the
     last discontinuity is indicated in iscsiSsnDiscontinuityTime."
 ::= { iscsiSessionStatsEntry 3 }

iscsiSsnRxDataOctets OBJECT-TYPE
  SYNTAX      Counter64
  UNITS       "octets"
  MAX-ACCESS  read-only
  STATUS      current

```

```

DESCRIPTION
"The count of data octets that were received by
the local iSCSI node on this session.
If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiSsnDiscontinuityTime."
 ::= { iscsiSessionStatsEntry 4 }

iscsiSsnLCTxDataOctets OBJECT-TYPE
  SYNTAX      Counter32
  UNITS       "octets"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "A Low-Capacity shadow object of iscsiSsnTxDataOctets
     for those systems that are accessible via SNMPv1 only.
     If this counter has suffered a discontinuity, the time of the
     last discontinuity is indicated in iscsiSsnDiscontinuityTime."
 ::= { iscsiSessionStatsEntry 5 }

iscsiSsnLCRxDataOctets OBJECT-TYPE
  SYNTAX      Counter32
  UNITS       "octets"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "A Low-Capacity shadow object of iscsiSsnRxDataOctets
     for those systems which are accessible via SNMPv1 only.
     If this counter has suffered a discontinuity, the time of the
     last discontinuity is indicated in iscsiSsnDiscontinuityTime."
 ::= { iscsiSessionStatsEntry 6 }

iscsiSsnNopReceivedPDUs OBJECT-TYPE
  SYNTAX      Counter32
  UNITS       "PDUs"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The count of NOP-In or NOP-Out PDUs received on this session.
     If this counter has suffered a discontinuity, the time of the
     last discontinuity is indicated in iscsiSsnDiscontinuityTime."
 ::= { iscsiSessionStatsEntry 7 }

iscsiSsnNopSentPDUs OBJECT-TYPE
  SYNTAX      Counter32
  UNITS       "PDUs"
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION

```

```

"The count of NOP-In or NOP-Out PDUs sent on this session.
If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiSsnDiscontinuityTime."
 ::= { iscsiSessionStatsEntry 8 }

-- Session Connection Error Stats Table

iscsiSessionCxnErrorStatsTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF IscsiSessionCxnErrorStatsEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "A list of error counters for each of the sessions
         present on this system."
 ::= { iscsiSession 3 }

iscsiSessionCxnErrorStatsEntry OBJECT-TYPE
    SYNTAX      IscsiSessionCxnErrorStatsEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "An entry (row) containing error counters for
         a particular session."
    AUGMENTS { iscsiSessionAttributesEntry }
 ::= { iscsiSessionCxnErrorStatsTable 1 }

IscsiSessionCxnErrorStatsEntry ::= SEQUENCE {
    iscsiSsnCxnDigestErrors      Counter32,
    iscsiSsnCxnTimeoutErrors     Counter32
}

iscsiSsnCxnDigestErrors OBJECT-TYPE
    SYNTAX      Counter32
    UNITS      "PDUs"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The count of PDUs that were received on the session and
         contained header or data digest errors.
        If this counter has suffered a discontinuity, the time of the
         last discontinuity is indicated in iscsiSsnDiscontinuityTime.
        This counter is most likely provided when the error-recovery
         level is 1 or 2"
    REFERENCE
        "RFC 7143, Section 7.8, Digest Errors"
 ::= { iscsiSessionCxnErrorStatsEntry 1 }

iscsiSsnCxnTimeoutErrors OBJECT-TYPE

```

```

SYNTAX      Counter32
UNITS      "connections"
MAX-ACCESS  read-only
STATUS     current
DESCRIPTION
    "The count of connections within this session
     that have been terminated due to timeout.
    If this counter has suffered a discontinuity, the time of the
     last discontinuity is indicated in iscsiSsnDiscontinuityTime.
     This counter is most likely provided when the error-recovery
     level is 2"
REFERENCE
    "RFC 7143, Section 7.5, Connection Timeout Management"
::= { iscsiSessionCxnErrorStatsEntry 2 }

--*****iscsiConnection OBJECT IDENTIFIER ::= { iscsiObjects 11 }

-- Connection Attributes Table

iscsiConnectionAttributesTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF IscsiConnectionAttributesEntry
    MAX-ACCESS  not-accessible
    STATUS     current
    DESCRIPTION
        "A list of connections belonging to each iSCSI instance
         present on the system."
::= { iscsiConnection 1 }

iscsiConnectionAttributesEntry OBJECT-TYPE
    SYNTAX      IscsiConnectionAttributesEntry
    MAX-ACCESS  not-accessible
    STATUS     current
    DESCRIPTION
        "An entry (row) containing management information applicable
         to a particular connection."
INDEX  { iscsiInstIndex, iscsiSsnNodeIndex, iscsiSsnIndex,
          iscsiCxnIndex }
::= { iscsiConnectionAttributesTable 1 }

IscsiConnectionAttributesEntry ::= SEQUENCE {
    iscsiCxnIndex          Unsigned32,
    iscsiCxnCid            Unsigned32,
    iscsiCxnState           INTEGER,
    iscsiCxnAddrType        InetAddressType,
    iscsiCxnLocalAddr       InetAddress,
    iscsiCxnProtocol        IscsiTransportProtocol,
}

```

```

iscsiCxnLocalPort          InetPortNumber,
iscsiCxnRemoteAddr         InetAddress,
iscsiCxnRemotePort         InetPortNumber,
iscsiCxnMaxRecvDataSegLength Unsigned32,
iscsiCxnMaxXmitDataSegLength Unsigned32,
iscsiCxnHeaderIntegrity    IscsiDigestMethod,
iscsiCxnDataIntegrity      IscsiDigestMethod,
iscsiCxnRecvMarker         TruthValue,
iscsiCxnSendMarker         TruthValue,
iscsiCxnVersionActive      Unsigned32
}

iscsiCxnIndex OBJECT-TYPE
  SYNTAX      Unsigned32 (1..4294967295)
  MAX-ACCESS  not-accessible
  STATUS      current
  DESCRIPTION
    "An arbitrary integer used to uniquely identify a
     particular connection of a particular session within
     an iSCSI instance present on the local system. An
     agent should attempt to not reuse index values unless
     a reboot has occurred. iSCSI connections are destroyed
     during a reboot; rows in this table are not persistent
     across reboots."
 ::= { iscsiConnectionAttributesEntry 1 }

iscsiCxnCid OBJECT-TYPE
  SYNTAX      Unsigned32 (1..65535)
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The iSCSI Connection ID for this connection."
 ::= { iscsiConnectionAttributesEntry 2 }

iscsiCxnState OBJECT-TYPE
  SYNTAX      INTEGER {
                login(1),
                full(2),
                logout(3)
              }
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The current state of this connection, from an iSCSI negotiation
     point of view. Here are the states:

      login - The transport protocol connection has been established,
              but a valid iSCSI login response with the final bit set

```

```

        has not been sent or received.
full    - A valid iSCSI login response with the final bit set
        has been sent or received.
logout - A valid iSCSI logout command has been sent or
        received, but the transport protocol connection has
        not yet been closed."
 ::= { iscsiConnectionAttributesEntry 3 }

iscsiCxnAddrType OBJECT-TYPE
  SYNTAX      InetAddressType
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The type of Internet Network Addresses contained in the
     corresponding instances of iscsiCxnLocalAddr and
     iscsiCxnRemoteAddr.
     The value 'dns' is not allowed."
 ::= { iscsiConnectionAttributesEntry 4 }

iscsiCxnLocalAddr OBJECT-TYPE
  SYNTAX      InetAddress
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The local Internet Network Address, of the type specified
     by iscsiCxnAddrType, used by this connection."
 ::= { iscsiConnectionAttributesEntry 5 }

iscsiCxnProtocol OBJECT-TYPE
  SYNTAX      IscsiTransportProtocol
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The transport protocol over which this connection is
     running."
 ::= { iscsiConnectionAttributesEntry 6 }

iscsiCxnLocalPort OBJECT-TYPE
  SYNTAX      InetPortNumber
  MAX-ACCESS  read-only
  STATUS      current
  DESCRIPTION
    "The local transport protocol port used by this connection.
     This object cannot have the value zero, since it represents
     an established connection."
 ::= { iscsiConnectionAttributesEntry 7 }

iscsiCxnRemoteAddr OBJECT-TYPE

```

```

SYNTAX          InetAddress
MAX-ACCESS     read-only
STATUS         current
DESCRIPTION
    "The remote Internet Network Address, of the type specified
     by iscsiCxnAddrType, used by this connection."
 ::= { iscsiConnectionAttributesEntry 8 }

iscsiCxnRemotePort OBJECT-TYPE
SYNTAX          InetPortNumber
MAX-ACCESS     read-only
STATUS         current
DESCRIPTION
    "The remote transport protocol port used by this connection.
     This object cannot have the value zero, since it represents
     an established connection."
 ::= { iscsiConnectionAttributesEntry 9 }

iscsiCxnMaxRecvDataSegLength OBJECT-TYPE
SYNTAX          Unsigned32 (512..16777215)
UNITS           "bytes"
MAX-ACCESS     read-only
STATUS         current
DESCRIPTION
    "The maximum data payload size supported for command
     or data PDUs able to be received on this connection."
REFERENCE
    "RFC 7143, Section 13.12, MaxRecvDataSegmentLength"
 ::= { iscsiConnectionAttributesEntry 10 }

iscsiCxnMaxXmitDataSegLength OBJECT-TYPE
SYNTAX          Unsigned32 (512..16777215)
UNITS           "bytes"
MAX-ACCESS     read-only
STATUS         current
DESCRIPTION
    "The maximum data payload size supported for command
     or data PDUs to be sent on this connection."
REFERENCE
    "RFC 7143, Section 13.12, MaxRecvDataSegmentLength"
 ::= { iscsiConnectionAttributesEntry 11 }

iscsiCxnHeaderIntegrity OBJECT-TYPE
SYNTAX          IscsiDigestMethod
MAX-ACCESS     read-only
STATUS         current
DESCRIPTION
    "This object identifies the iSCSI header"

```

```

digest scheme in use within this connection."
 ::= { iscsiConnectionAttributesEntry 12 }

iscsiCxnDataIntegrity OBJECT-TYPE
    SYNTAX          IscsiDigestMethod
    MAX-ACCESS     read-only
    STATUS         current
    DESCRIPTION
        "This object identifies the iSCSI data
         digest scheme in use within this connection."
 ::= { iscsiConnectionAttributesEntry 13 }

iscsiCxnRecvMarker OBJECT-TYPE
    SYNTAX          TruthValue
    MAX-ACCESS     read-only
    STATUS         deprecated
    DESCRIPTION
        "This object indicates whether or not this connection
         is receiving markers in its incoming data stream."
    REFERENCE
        "RFC 7143, Section 13.25, Obsoleted Keys."
 ::= { iscsiConnectionAttributesEntry 14 }

iscsiCxnSendMarker OBJECT-TYPE
    SYNTAX          TruthValue
    MAX-ACCESS     read-only
    STATUS         deprecated
    DESCRIPTION
        "This object indicates whether or not this connection
         is inserting markers in its outgoing data stream."
    REFERENCE
        "RFC 7143, Section 13.25, Obsoleted Keys."
 ::= { iscsiConnectionAttributesEntry 15 }

iscsiCxnVersionActive OBJECT-TYPE
    SYNTAX          Unsigned32 (0..255)
    MAX-ACCESS     read-only
    STATUS         current
    DESCRIPTION
        "Active version number of the iSCSI specification negotiated
         on this connection."
    REFERENCE
        "RFC 7143, Section 11.12, Login Request"
 ::= { iscsiConnectionAttributesEntry 16 }

*****  

-- Notifications

```

```

iscsiTgtLoginFailure NOTIFICATION-TYPE
OBJECTS {
    iscsiTgtLoginFailures,
    iscsiTgtLastFailureType,
    iscsiTgtLastIntrFailureName,
    iscsiTgtLastIntrFailureAddrType,
    iscsiTgtLastIntrFailureAddr,
    iscsiTgtLastIntrFailurePort
}
STATUS current
DESCRIPTION
    "Sent when a login is failed by a target.

To avoid sending an excessive number of notifications due
to multiple errors counted, an SNMP agent implementing this
notification SHOULD NOT send more than 3 notifications of
this type in any 10-second time period."
 ::= { iscsiNotifications 1 }

iscsiIntrLoginFailure NOTIFICATION-TYPE
OBJECTS {
    iscsiIntrLoginFailures,
    iscsiIntrLastFailureType,
    iscsiIntrLastTgtFailureName,
    iscsiIntrLastTgtFailureAddrType,
    iscsiIntrLastTgtFailureAddr,
    iscsiIntrLastTgtFailurePort
}
STATUS current
DESCRIPTION
    "Sent when a login is failed by an initiator.

To avoid sending an excessive number of notifications due
to multiple errors counted, an SNMP agent implementing this
notification SHOULD NOT send more than 3 notifications of
this type in any 10-second time period."
 ::= { iscsiNotifications 2 }

iscsiInstSessionFailure NOTIFICATION-TYPE
OBJECTS {
    iscsiInstSsnFailures,
    iscsiInstLastSsnFailureType,
    iscsiInstLastSsnRmtNodeName
}
STATUS current
DESCRIPTION
    "Sent when an active session is failed by either the initiator
or the target.

```

```

To avoid sending an excessive number of notifications due
to multiple errors counted, an SNMP agent implementing this
notification SHOULD NOT send more than 3 notifications of
this type in any 10-second time period."
 ::= { iscsiNotifications 3 }

-- ****
-- Conformance Statements

iscsiCompliances OBJECT IDENTIFIER ::= { iscsiConformance 1 }
iscsiGroups      OBJECT IDENTIFIER ::= { iscsiConformance 2 }

iscsiInstanceAttributesGroup OBJECT-GROUP
OBJECTS {
    iscsiInstDescr,
    iscsiInstVersionMin,
    iscsiInstVersionMax,
    iscsiInstVendorID,
    iscsiInstVendorVersion,
    iscsiInstPortalNumber,
    iscsiInstNodeNumber,
    iscsiInstSessionNumber,
    iscsiInstSsnFailures,
    iscsiInstLastSsnFailureType,
    iscsiInstLastSsnRmtNodeName,
    iscsiInstDiscontinuityTime,
    iscsiInstXNodeArchitecture
}
STATUS current
DESCRIPTION
    "A collection of objects providing information about iSCSI
     instances."
 ::= { iscsiGroups 1 }

iscsiInstanceSsnErrorStatsGroup OBJECT-GROUP
OBJECTS {
    iscsiInstSsnDigestErrors,
    iscsiInstSsnCxnTimeoutErrors,
    iscsiInstSsnFormatErrors
}
STATUS current
DESCRIPTION
    "A collection of objects providing information about
     errors that have caused a session failure for an
     iSCSI instance."
 ::= { iscsiGroups 2 }

```

```

iscsiPortalAttributesGroup OBJECT-GROUP
  OBJECTS {
    iscsiPortalRowStatus,
    iscsiPortalStorageType,
    iscsiPortalRoles,
    iscsiPortalAddrType,
    iscsiPortalAddr,
    iscsiPortalProtocol,
    iscsiPortalMaxRecvDataSegLength,
    iscsiPortalPrimaryHdrDigest,
    iscsiPortalPrimaryDataDigest,
    iscsiPortalSecondaryHdrDigest,
    iscsiPortalSecondaryDataDigest,
    iscsiPortalRecvMarker
  }
  STATUS deprecated
  DESCRIPTION
    "A collection of objects providing information about
     the transport protocol endpoints of the local targets.
     This object group is deprecated because the marker key
     is obsolete."
  REFERENCE
    "RFC 7143, Section 13.25, Obsoleted Keys."
 ::= { iscsiGroups 3 }

iscsiTgtPortalAttributesGroup OBJECT-GROUP
  OBJECTS {
    iscsiTgtPortalPort,
    iscsiTgtPortalTag
  }
  STATUS current
  DESCRIPTION
    "A collection of objects providing information about
     the transport protocol endpoints of the local targets."
 ::= { iscsiGroups 4 }

iscsiIntrPortalAttributesGroup OBJECT-GROUP
  OBJECTS {
    iscsiIntrPortalTag
  }
  STATUS current
  DESCRIPTION
    "An object providing information about
     the portal tags used by the local initiators."
 ::= { iscsiGroups 5 }

iscsiNodeAttributesGroup OBJECT-GROUP
  OBJECTS {

```

```

    iscsiNodeName,
    iscsiNodeAlias,
    iscsiNodeRoles,
    iscsiNodeTransportType,
    iscsiNodeInitialR2T,
    iscsiNodeImmediateData,
    iscsiNodeMaxOutstandingR2T,
    iscsiNodeFirstBurstLength,
    iscsiNodeMaxBurstLength,
    iscsiNodeMaxConnections,
    iscsiNodeDataSequenceInOrder,
    iscsiNodeDataPDUInOrder,
    iscsiNodeDefaultTime2Wait,
    iscsiNodeDefaultTime2Retain,
    iscsiNodeErrorRecoveryLevel,
    iscsiNodeDiscontinuityTime,
    iscsiNodeStorageType
}
STATUS current
DESCRIPTION
  "A collection of objects providing information about all
  local targets."
 ::= { iscsiGroups 6 }

iscsiTargetAttributesGroup OBJECT-GROUP
  OBJECTS {
    iscsiTgtLoginFailures,
    iscsiTgtLastFailureTime,
    iscsiTgtLastFailureType,
    iscsiTgtLastIntrFailureName,
    iscsiTgtLastIntrFailureAddrType,
    iscsiTgtLastIntrFailureAddr
  }
  STATUS current
  DESCRIPTION
    "A collection of objects providing information about all
    local targets."
 ::= { iscsiGroups 7 }

iscsiTargetLoginStatsGroup OBJECT-GROUP
  OBJECTS {
    iscsiTgtLoginAccepts,
    iscsiTgtLoginOtherFails,
    iscsiTgtLoginRedirects,
    iscsiTgtLoginAuthorizeFails,
    iscsiTgtLoginAuthenticateFails,
    iscsiTgtLoginNegotiateFails
  }

```

```

STATUS current
DESCRIPTION
    "A collection of objects providing information about all
    login attempts by remote initiators to local targets."
 ::= { iscsiGroups 8 }

iscsiTargetLogoutStatsGroup OBJECT-GROUP
    OBJECTS {
        iscsiTgtLogoutNormals,
        iscsiTgtLogoutOthers
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about all
        logout events between remote initiators and local targets."
 ::= { iscsiGroups 9 }

iscsiTargetAuthGroup OBJECT-GROUP
    OBJECTS {
        iscsiTgtAuthRowStatus,
        iscsiTgtAuthStorageType,
        iscsiTgtAuthIdentity
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about all
        remote initiators that are authorized to connect to local
        targets."
 ::= { iscsiGroups 10 }

iscsiInitiatorAttributesGroup OBJECT-GROUP
    OBJECTS {
        iscsiIntrLoginFailures,
        iscsiIntrLastFailureTime,
        iscsiIntrLastFailureType,
        iscsiIntrLastTgtFailureName,
        iscsiIntrLastTgtFailureAddrType,
        iscsiIntrLastTgtFailureAddr
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about
        all local initiators."
 ::= { iscsiGroups 11 }

iscsiInitiatorLoginStatsGroup OBJECT-GROUP
    OBJECTS {
        iscsiIntrLoginAcceptRsp,

```

```

    iscsiIntrLoginOtherFailRsp,
    iscsiIntrLoginRedirectRsp,
    iscsiIntrLoginAuthFailRsp,
    iscsiIntrLoginAuthenticateFails,
    iscsiIntrLoginNegotiateFails,
    iscsiIntrLoginAuthorizeFails
}
STATUS current
DESCRIPTION
  "A collection of objects providing information about all
  login attempts by local initiators to remote targets."
::= { iscsiGroups 12 }

iscsiInitiatorLogoutStatsGroup OBJECT-GROUP
  OBJECTS {
    iscsiIntrLogoutNormals,
    iscsiIntrLogoutOthers
}
STATUS current
DESCRIPTION
  "A collection of objects providing information about all
  logout events between local initiators and remote targets."
::= { iscsiGroups 13 }

iscsiInitiatorAuthGroup OBJECT-GROUP
  OBJECTS {
    iscsiIntrAuthRowStatus,
    iscsiIntrAuthStorageType,
    iscsiIntrAuthIdentity
}
STATUS current
DESCRIPTION
  "A collection of objects providing information about all
  remote targets that are initiators of the local system
  that they are authorized to access."
::= { iscsiGroups 14 }

iscsiSessionAttributesGroup OBJECT-GROUP
  OBJECTS {
    iscsiSsnDirection,
    iscsiSsnInitiatorName,
    iscsiSsnTargetName,
    iscsiSsnTSIH,
    iscsiSsnISID,
    iscsiSsnInitiatorAlias,
    iscsiSsnTargetAlias,
    iscsiSsnInitialR2T,
    iscsiSsnImmediateData,

```

```

    iscsiSsnType,
    iscsiSsnMaxOutstandingR2T,
    iscsiSsnFirstBurstLength,
    iscsiSsnMaxBurstLength,
    iscsiSsnConnectionNumber,
    iscsiSsnAuthIdentity,
    iscsiSsnDataSequenceInOrder,
    iscsiSsnDataPDUInOrder,
    iscsiSsnErrorRecoveryLevel,
    iscsiSsnDiscontinuityTime,
    iscsiSsnProtocolLevel,
    iscsiSsnTaskReporting
}
STATUS current
DESCRIPTION
  "A collection of objects providing information applicable to
   all sessions."
 ::= { iscsiGroups 15 }

iscsiSessionPDUMstatsGroup OBJECT-GROUP
  OBJECTS {
    iscsiSsnCmdPDUs,
    iscsiSsnRspPDUs
  }
  STATUS current
  DESCRIPTION
    "A collection of objects providing information about PDU
     traffic for each session."
 ::= { iscsiGroups 16 }

iscsiSessionOctetStatsGroup OBJECT-GROUP
  OBJECTS {
    iscsiSsnTxDataOctets,
    iscsiSsnRxDataOctets
  }
  STATUS current
  DESCRIPTION
    "A collection of objects providing information about octet
     traffic for each session using a Counter64 data type."
 ::= { iscsiGroups 17 }

iscsiSessionLCOctetStatsGroup OBJECT-GROUP
  OBJECTS {
    iscsiSsnLCTxDataOctets,
    iscsiSsnLCRxDataOctets
  }
  STATUS current
  DESCRIPTION

```

```

    "A collection of objects providing information about octet
    traffic for each session using a Counter32 data type."
 ::= { iscsiGroups 18 }

iscsiSessionCxnErrorStatsGroup OBJECT-GROUP
  OBJECTS {
    iscsiSsnCxnDigestErrors,
    iscsiSsnCxnTimeoutErrors
  }
  STATUS current
  DESCRIPTION
    "A collection of objects providing information about connection
    errors for all sessions."
 ::= { iscsiGroups 19 }

iscsiConnectionAttributesGroup OBJECT-GROUP
  OBJECTS {
    iscsiCxnCid,
    iscsiCxnState,
    iscsiCxnProtocol,
    iscsiCxnAddrType,
    iscsiCxnLocalAddr,
    iscsiCxnLocalPort,
    iscsiCxnRemoteAddr,
    iscsiCxnRemotePort,
    iscsiCxnMaxRecvDataSegLength,
    iscsiCxnMaxXmitDataSegLength,
    iscsiCxnHeaderIntegrity,
    iscsiCxnDataIntegrity,
    iscsiCxnRecvMarker,
    iscsiCxnSendMarker,
    iscsiCxnVersionActive
  }
  STATUS deprecated
  DESCRIPTION
    "A collection of objects providing information about all
    connections used by all sessions.
    This object group is deprecated because the marker key
    is obsolete."
  REFERENCE
    "RFC 7143, Section 13.25, Obsoleted Keys."
 ::= { iscsiGroups 20 }

iscsiTgtLgnNotificationsGroup NOTIFICATION-GROUP
  NOTIFICATIONS {
    iscsiTgtLoginFailure
  }
  STATUS current

```

```

DESCRIPTION
    "A collection of notifications that indicate a login
     failure from a remote initiator to a local target."
 ::= { iscsiGroups 21 }

iscsiIntrLgnNotificationsGroup NOTIFICATION-GROUP
    NOTIFICATIONS {
        iscsiIntrLoginFailure
    }
    STATUS current
DESCRIPTION
    "A collection of notifications that indicate a login
     failure from a local initiator to a remote target."
 ::= { iscsiGroups 22 }

iscsiSsnFlrNotificationsGroup NOTIFICATION-GROUP
    NOTIFICATIONS {
        iscsiInstSessionFailure
    }
    STATUS current
DESCRIPTION
    "A collection of notifications that indicate session
     failures occurring after login."
 ::= { iscsiGroups 23 }

iscsiPortalAttributesGroupV2 OBJECT-GROUP
    OBJECTS {
        iscsiPortalRowStatus,
        iscsiPortalStorageType,
        iscsiPortalRoles,
        iscsiPortalAddrType,
        iscsiPortalAddr,
        iscsiPortalProtocol,
        iscsiPortalMaxRecvDataSegLength,
        iscsiPortalPrimaryHdrDigest,
        iscsiPortalPrimaryDataDigest,
        iscsiPortalSecondaryHdrDigest,
        iscsiPortalSecondaryDataDigest
    }
    STATUS current
DESCRIPTION
    "A collection of objects providing information about
     the transport protocol endpoints of the local targets."
 ::= { iscsiGroups 24 }

iscsiConnectionAttributesGroupV2 OBJECT-GROUP
    OBJECTS {
        iscsiCxnCid,

```

```

    iscsiCxnState,
    iscsiCxnProtocol,
    iscsiCxnAddrType,
    iscsiCxnLocalAddr,
    iscsiCxnLocalPort,
    iscsiCxnRemoteAddr,
    iscsiCxnRemotePort,
    iscsiCxnMaxRecvDataSegLength,
    iscsiCxnMaxXmitDataSegLength,
    iscsiCxnHeaderIntegrity,
    iscsiCxnDataIntegrity,
    iscsiCxnVersionActive
}

STATUS current
DESCRIPTION
  "A collection of objects providing information about all
  connections used by all sessions."
 ::= { iscsiGroups 25 }

iscsiNewObjectsV2 OBJECT-GROUP
  OBJECTS {
    iscsiInstXNodeArchitecture,
    iscsiSsnTaskReporting,
    iscsiSsnProtocolLevel,
    iscsiSsnNopReceivedPDUs,
    iscsiSsnNopSentPDUs,
    iscsiIntrLastTgtFailurePort,
    iscsiTgtLastIntrFailurePort,
    iscsiPortalDescr,
    iscsiInstSsnTgtUnmappedErrors,
    iscsiTgtLogoutCxnClosed,
    iscsiTgtLogoutCxnRemoved
}
}

STATUS current
DESCRIPTION
  "A collection of objects added in the second version of the
  iSCSI MIB."
 ::= { iscsiGroups 26 }

*****  

iscsiComplianceV1 MODULE-COMPLIANCE
  STATUS deprecated
  DESCRIPTION
    "Initial version of compliance statement.

```

If an implementation can be both a target and an initiator, all groups are mandatory.  
 This module compliance is deprecated because the marker keys are obsolete."

**REFERENCE**  
 "RFC 7143, Section 13.25, Obsoleted Keys."

**MODULE** -- this module

**MANDATORY-GROUPS {**

- iscsiInstanceAttributesGroup,
- iscsiInstanceSsnErrorStatsGroup,
- iscsiPortalAttributesGroup,
- iscsiNodeAttributesGroup,
- iscsiSessionAttributesGroup,
- iscsiSessionPDUStatsGroup,
- iscsiSessionCxnErrorStatsGroup,
- iscsiConnectionAttributesGroup,
- iscsiSsnFlrNotificationsGroup

**}**

-- Conditionally mandatory groups depending on the ability  
 -- to support Counter64 data types and/or to provide counter  
 -- information to SNMPv1 applications.

**GROUP iscsiSessionOctetStatsGroup**

**DESCRIPTION**  
 "This group is mandatory for all iSCSI implementations  
 that can support Counter64 data types."

**GROUP iscsiSessionLCOctetStatsGroup**

**DESCRIPTION**  
 "This group is mandatory for all iSCSI implementations  
 that provide information to SNMPv1-only applications;  
 this includes agents that cannot support Counter64  
 data types."

-- Conditionally mandatory groups to be included with  
 -- the mandatory groups when the implementation has  
 -- iSCSI target facilities.

**GROUP iscsiTgtPortalAttributesGroup**

**DESCRIPTION**  
 "This group is mandatory for all iSCSI implementations  
 that have iSCSI target facilities."

**OBJECT iscsiPortalMaxRecvDataSegLength**

**MIN-ACCESS** read-only

**DESCRIPTION**  
 "Write access is not required."

```
OBJECT iscsiNodeStorageType
MIN-ACCESS read-only
DESCRIPTION
  "Write access is not required; an implementation may
   choose to allow this object to be set to 'volatile'
   or 'nonVolatile'.""
GROUP iscsiTargetAttributesGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI target facilities."

GROUP iscsiTargetLoginStatsGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI target facilities."

GROUP iscsiTargetLogoutStatsGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI target facilities."

GROUP iscsiTgtLgnNotificationsGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI target facilities."

GROUP iscsiTargetAuthGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI target facilities."
-- Conditionally mandatory groups to be included with
-- the mandatory groups when the implementation has
-- iSCSI initiator facilities.

GROUP iscsiIntrPortalAttributesGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI initiator facilities."

GROUP iscsiInitiatorAttributesGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI initiator facilities."

GROUP iscsiInitiatorLoginStatsGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
```

```

that have iSCSI initiator facilities."}

GROUP iscsiInitiatorLogoutStatsGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI initiator facilities."

GROUP iscsiIntrLgnNotificationsGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI initiator facilities."

GROUP iscsiInitiatorAuthGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI initiator facilities.

OBJECT      iscsiNodeErrorRecoveryLevel
SYNTAX      Unsigned32 (0..2)
DESCRIPTION
  "Only values 0-2 are defined at present.

 ::= { iscsiCompliances 1 }

iscsiComplianceV2 MODULE-COMPLIANCE
  STATUS current
  DESCRIPTION
    "Version 2 of compliance statement based on
     this revised version of the MIB module.

    If an implementation can be both a target and an
    initiator, all groups are mandatory."
  MODULE      -- this module
  MANDATORY-GROUPS {
    iscsiInstanceAttributesGroup,
    iscsiInstanceSsnErrorStatsGroup,
    iscsiPortalAttributesGroupV2,
    iscsiNodeAttributesGroup,
    iscsiSessionAttributesGroup,
    iscsiSessionPDUStatsGroup,
    iscsiSessionCxnErrorStatsGroup,
    iscsiConnectionAttributesGroupV2,
    iscsiSsnFlrNotificationsGroup
  }
  -- Conditionally mandatory groups depending on the ability
  -- to support Counter64 data types and/or to provide counter
  -- information to SNMPv1 applications.

```

```
GROUP iscsiSessionOctetStatsGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that can support Counter64 data types."

GROUP iscsiSessionLCOctetStatsGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that provide information to SNMPv1-only applications;
   this includes agents that cannot support Counter64
   data types.

-- Conditionally mandatory groups to be included with
-- the mandatory groups when the implementation has
-- iSCSI target facilities.

GROUP iscsiTgtPortalAttributesGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI target facilities.

OBJECT iscsiPortalMaxRecvDataSegLength
MIN-ACCESS read-only
DESCRIPTION
  "Write access is not required."

OBJECT iscsiNodeStorageType
MIN-ACCESS read-only
DESCRIPTION
  "Write access is not required; an implementation may
   choose to allow this object to be set to 'volatile'
   or 'nonVolatile'."

GROUP iscsiTargetAttributesGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI target facilities.

GROUP iscsiTargetLoginStatsGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI target facilities.

GROUP iscsiTargetLogoutStatsGroup
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that have iSCSI target facilities."
```

```
GROUP iscsiTgtLgnNotificationsGroup
DESCRIPTION
    "This group is mandatory for all iSCSI implementations
     that have iSCSI target facilities."

GROUP iscsiTargetAuthGroup
DESCRIPTION
    "This group is mandatory for all iSCSI implementations
     that have iSCSI target facilities.

-- Conditionally mandatory groups to be included with
-- the mandatory groups when the implementation has
-- iSCSI initiator facilities.

GROUP iscsiIntrPortalAttributesGroup
DESCRIPTION
    "This group is mandatory for all iSCSI implementations
     that have iSCSI initiator facilities.

GROUP iscsiInitiatorAttributesGroup
DESCRIPTION
    "This group is mandatory for all iSCSI implementations
     that have iSCSI initiator facilities.

GROUP iscsiInitiatorLoginStatsGroup
DESCRIPTION
    "This group is mandatory for all iSCSI implementations
     that have iSCSI initiator facilities.

GROUP iscsiInitiatorLogoutStatsGroup
DESCRIPTION
    "This group is mandatory for all iSCSI implementations
     that have iSCSI initiator facilities.

GROUP iscsiIntrLgnNotificationsGroup
DESCRIPTION
    "This group is mandatory for all iSCSI implementations
     that have iSCSI initiator facilities.

GROUP iscsiInitiatorAuthGroup
DESCRIPTION
    "This group is mandatory for all iSCSI implementations
     that have iSCSI initiator facilities.

OBJECT      iscsiNodeErrorRecoveryLevel
SYNTAX      Unsigned32 (0..2)
DESCRIPTION
    "Only values 0-2 are defined at present."
```

```
GROUP iscsiNewObjectsV2
DESCRIPTION
  "This group is mandatory for all iSCSI implementations
   that support a value of the iSCSIProtocolLevel key of
   2 or greater."
 ::= { iscsiCompliances 2 }

END
```

## 8. Security Considerations

There are a number of management objects defined in this MIB module with a MAX-ACCESS clause of read-write and/or read-create. Such objects may be considered sensitive or vulnerable in some network environments. The support for SET operations in a non-secure environment without proper protection can have a negative effect on network operations. These are the tables and objects and their sensitivity/vulnerability:

`iscsiPortalAttributesTable`, `iscsiTgtPortalAttributesTable`, and `iscsiIntrPortalAttributesTable` can be used to add or remove IP addresses to be used by iSCSI.

`iscsiTgtAuthAttributesTable` entries can be added or removed, to allow or disallow access to a target by an initiator.

Some of the readable objects in this MIB module (i.e., objects with a MAX-ACCESS other than not-accessible) may be considered sensitive or vulnerable in some network environments. It is thus important to control even GET and/or NOTIFY access to these objects and possibly to even encrypt the values of these objects when sending them over the network via SNMP. These are the tables and objects and their sensitivity/vulnerability:

`iscsiNodeAttributesTable`, `iscsiTargetAttributesTable`, and `iscsiTgtAuthorization` can be used to glean information needed to make connections to the iSCSI targets this module represents. However, it is the responsibility of the initiators and targets involved to authenticate each other to ensure that an inappropriately advertised or discovered initiator or target does not compromise their security. These issues are discussed in [RFC7143].

SNMP versions prior to SNMPv3 did not include adequate security. Even if the network itself is secure (for example by using IPsec), even then, there is no control as to who on the secure network is allowed to access and GET/SET (read/change/create/delete) the objects in this MIB module.

Implementations SHOULD provide the security features described by the SNMPv3 framework (see [RFC3410]), and implementations claiming compliance to the SNMPv3 standard MUST include full support for authentication and privacy via the User-based Security Model (USM) [RFC3414] with the AES cipher algorithm [RFC3826]. Implementations MAY also provide support for the Transport Security Model (TSM) [RFC5591] in combination with a secure transport such as SSH [RFC5592] or TLS/DTLS [RFC6353].

Further, deployment of SNMP versions prior to SNMPv3 is NOT RECOMMENDED. Instead, it is RECOMMENDED to deploy SNMPv3 and to enable cryptographic security. It is then a customer/operator responsibility to ensure that the SNMP entity giving access to an instance of this MIB module is properly configured to give access to the objects only to those principals (users) that have legitimate rights to indeed GET or SET (change/create/delete) them.

## 9. IANA Considerations

The MIB module in this document uses the following IANA-assigned OBJECT IDENTIFIER value recorded in the "SMI Network Management MGMT Codes Internet-standard MIB" registry:

Descriptor	OBJECT IDENTIFIER value
-----	-----
iscsiMibModule	{ mib-2 142 }

IANA has updated the reference for the mib-2 142 identifier to refer to this document.

## 10. References

### 10.1. Normative References

- [RFC2119] Bradner, S., "Key words for use in RFCs to Indicate Requirement Levels", BCP 14, RFC 2119, March 1997.
- [RFC2578] McCloghrie, K., Ed., Perkins, D., Ed., and J. Schoenwaelder, Ed., "Structure of Management Information Version 2 (SMIV2)", STD 58, RFC 2578, April 1999.

- [RFC2579] McCloghrie, K., Ed., Perkins, D., Ed., and J. Schoenwaelder, Ed., "Textual Conventions for SMIv2", STD 58, RFC 2579, April 1999.
- [RFC2580] McCloghrie, K., Ed., Perkins, D., Ed., and J. Schoenwaelder, Ed., "Conformance Statements for SMIv2", STD 58, RFC 2580, April 1999.
- [RFC3411] Harrington, D., Presuhn, R., and B. Wijnen, "An Architecture for Describing Simple Network Management Protocol (SNMP) Management Frameworks", STD 62, RFC 3411, December 2002.
- [RFC3414] Blumenthal, U. and B. Wijnen, "User-based Security Model (USM) for version 3 of the Simple Network Management Protocol (SNMPv3)", STD 62, RFC 3414, December 2002.
- [RFC3720] Satran, J., Meth, K., Sapuntzakis, C., Chadalapaka, M., and E. Zeidner, "Internet Small Computer Systems Interface (iSCSI)", RFC 3720, April 2004.
- [RFC3826] Blumenthal, U., Maino, F., and K. McCloghrie, "The Advanced Encryption Standard (AES) Cipher Algorithm in the SNMP User-based Security Model", RFC 3826, June 2004.
- [RFC4001] Daniele, M., Haberman, B., Routhier, S., and J. Schoenwaelder, "Textual Conventions for Internet Network Addresses", RFC 4001, February 2005.
- [RFC4545] Bakke, M. and J. Muchow, "Definitions of Managed Objects for IP Storage User Identity Authorization", RFC 4545, May 2006.
- [RFC5591] Harrington, D. and W. Hardaker, "Transport Security Model for the Simple Network Management Protocol (SNMP)", RFC 5591, June 2009.
- [RFC5592] Harrington, D., Salowey, J., and W. Hardaker, "Secure Shell Transport Model for the Simple Network Management Protocol (SNMP)", RFC 5592, June 2009.
- [RFC6353] Hardaker, W., "Transport Layer Security (TLS) Transport Model for the Simple Network Management Protocol (SNMP)", RFC 6353, July 2011.
- [RFC7143] Chadalapaka, M., Satran, J., Meth, K., and D. Black, "Internet Small Computer System Interface (iSCSI) Protocol (Consolidated)", RFC 7143, April 2014.

[RFC7144] Knight, F. and M. Chadalapaka, "Internet Small Computer System Interface (iSCSI) SCSI Features Update", RFC 7144, April 2014.

#### 10.2. Informative References

- [RFC3410] Case, J., Mundy, R., Partain, D., and B. Stewart, "Introduction and Applicability Statements for Internet-Standard Management Framework", RFC 3410, December 2002.
- [RFC4022] Raghunarayan, R., Ed., "Management Information Base for the Transmission Control Protocol (TCP)", RFC 4022, March 2005.
- [RFC4455] Hallak-Stamler, M., Bakke, M., Lederman, Y., Krueger, M., and K. McCloghrie, "Definition of Managed Objects for Small Computer System Interface (SCSI) Entities", RFC 4455, April 2006.
- [RFC4544] Bakke, M., Krueger, M., McSweeney, T., and J. Muchow, "Definitions of Managed Objects for Internet Small Computer System Interface (iSCSI)", RFC 4544, May 2006.

#### 11. Acknowledgments

The contents of this document were largely written as RFC 4544 by Mark Bakke (Cisco), Marjorie Krueger (Hewlett-Packard), Tom McSweeney (IBM), and James Muchow (QLogic). A special thank you to Marjorie, Tom, and James for their hard work and especially to James for his attention to detail on this work.

In addition to the authors, several people contributed to the development of this MIB module. Thanks especially to those who took the time to participate in our weekly conference calls to build our requirements, object models, table structures, and attributes: John Hufford, Tom McSweeney (IBM), Kevin Gibbons (Nishan Systems), Chad Gregory (Intel), Jack Harwood (EMC), Hari Mudaliar (Adaptec), Ie Wei Njoo (Agilent), Lawrence Lamers (SAN Valley), Satish Mali (Stonefly Networks), and William Terrell (Troika).

Special thanks to Tom McSweeney, Ie Wei Njoo, and Kevin Gibbons, who wrote the descriptions for many of the tables and attributes in this MIB module, to Ayman Ghanem for finding and suggesting changes for many problems in this module, and to Keith McCloghrie for serving as advisor to the team.

Thanks to Mike MacFaden (VMWare), David Black (EMC), and Tom Talpey (Microsoft) for their valuable inputs.

**Authors' Addresses**

Mark Bakke  
Dell  
7625 Smetana Lane  
Eden Prairie, MN 55344  
USA

EMail: [mark\\_bakke@dell.com](mailto:mark_bakke@dell.com)

Prakash Venkatesen  
HCL Technologies Ltd.  
50-53, Greams Road,  
Chennai - 600006  
India

EMail: [prakashvn@hcl.com](mailto:prakashvn@hcl.com)